/inritsu

MS2690A/MS2691A/MS2692A

-

10010010010

Signal Analyzer

MS2690A: 50 Hz to 6.0 GHz MS2691A: 50 Hz to 13.5 GHz MS2692A: 50 Hz to 26.5 GHz

Anritsu MS2690A

Ramote Local

3

ane.)

ILIDIORION



Andready Contraction Contraction



The MS2690A/MS2691A/MS2692A (MS269xA) Signal Analyzer has the excellent general level accuracy, dynamic range and performance of a high-end spectrum analyzer. Its easy operability and built-in functions are perfect for tests of Tx characteristics. Not only can it capture wideband signals but FFT technology supports multifunction signal analyses in both the time and frequency domains. Behavior in the time domain that cannot be handled by a sweep type spectrum analyzer can be checked in the frequency domain. A wide frequency can be analyzed using sweep type spectrum analysis functions while detailed signal analysis of a specific frequency band is supported too. Moreover, the built-in signal generator function outputs both continuous wave (CW) and modulated signals for use as a reference signal source when testing Tx characteristics of parts and as a signal source for evaluating Rx characteristics.

Wireless communications are tending toward use of higher frequencies above 3 GHz and wider bandwidths. However, general-purpose spectrum analyzers suffer from a degraded noise floor above 3 GHz due to the 3-GHz baseband, so they cannot be used to verify the true product performance. Because the MS269xA baseband can be extended up to 6 GHz it offers excellent level accuracy and modulation precision at frequencies from 50 Hz to 6 GHz. Adding the full line of versatile analysis software options eliminates the need for an external PC at wireless modulation analysis. Moreover, installing a preselector bypass option (MS2692A-067) enables use of the signal analyzer and modulation analysis functions up to 26.5 GHz (MS2692A). Waveform creation software generates modulation signal patterns for all common wireless technologies to output signals for the vector signal generator function. The high-performance, multi-function MS269xA Signal Analyzer supports better analysis than more expensive standalone spectrum analyzers.

MS2690A/MS2691A/MS2692A

Signal Analyzer MS2690A: 50 Hz to 6.0 GHz MS2691A: 50 Hz to 13.5 GHz MS2692A: 50 Hz to 26.5 GHz



Key Features



Basic Performance/Functions

Frequency Range

MS2690A: 50 Hz to 6.0 GHz MS2691A: 50 Hz to 13.5 GHz MS2692A: 50 Hz to 26.5 GHz

Total Level Accuracy: ±0.3 dB (typ.)

The Absolute Amplitude Accuracy specification described in catalogs of other spectrum analyzers ignores the important frequency characteristics, linearity, and attenuator switching errors. The MS269xA calibration technology supports excellent level accuracy over the wide frequency range from 50 Hz to 6 GHz even under measurement conditions including the above three errors.

Dynamic Range^{*1}: 177 dB

TOI*2: ≥+22 dBm

DANL*3: -155 dBm/Hz

Improved Level Linearity

Internal Reference Oscillator

Pre-installed Reference Oscillator

Aging Rate: ±1 × 10⁻⁸/day

Start-up Characteristics: $\pm 5 \times 10^{-8}$ (5 minutes after power-on) Rubidium Reference Oscillator (Opt. 001) Aging Rate: $\pm 1 \times 10^{-10}$ /month

Start-up Characteristics: ±1 × 10⁻⁹ (7 minutes after power-on)

Versatile Built-in Functions

[Standard]

- Channel Power
- Occupied Bandwidth
- Adjacent Channel Leakage Power
- Spectrum Emission Mask*4
- Spurious Emission*4
- Burst Average Power
- Frequency Counter*4
- AM Depth*5
- FM Deviation*5
- Multi-marker & Marker List - Highest 10 Markers
- Hignest 10 P
- Limit Line*4
- 2-tone 3rd-order Intermodulation Distortion*4
- Phase Noise
 Power Meter^{*6}

[Option]

- Noise Figure*7

Signal Analyzer Functions

Analysis Bandwidth

Standard: 31.25 MHz max.

(50 MHz max. sampling rate = 20 ns resolution, ADC resolution 16 bits) Opt. 077: 62.5 MHz max.

(100 MHz max. sampling rate = 10 ns resolution, ADC resolution 14 bits) Opt. 078^{*8, *9,:} 125 MHz max.

(200 MHz max. sampling rate = 5 ns resolution, ADC resolution 14 bits)

Capture Function

Saves analysis Span \times Time signal to internal memory and writes to hard disk.

Up to 100 Msamples per measurement can be saved to internal memory.

- Examples: Span 1 MHz: Max. capture time 50 s Span 10 MHz: Max. capture time 5 s
 - Span 100 MHz: Max. capture time 0.5 s

Replay Function

Reads saved data and replays using signal analyzer function. Examples:

- 1. Data sharing between separate R&D and manufacturing
- 2. Later laboratory bench-top analysis of on-site signals

Measurement with Sub-trace Display

Splits screen and confirms both main and sub-traces at same time to check errors.

- Main: Spectrum, Frequency vs. Time, Power vs. Time, Phase vs. Time, CCDF/APD, Spectrogram
- Sub: Power vs. Time, Spectrogram
- Supports 125 MHz Wideband Measurements up to 26.5 GHz Opt. 067 Microwave Preselector Bypass^{*10}

Opt. 078 Analysis Bandwidth Extension to 125 MHz*8

Bypassing preselector improves RF frequency characteristics and in-band frequency characteristics. Supports modulation analysis and signal analyzer measurements for signals up to 26.5 GHz.

Vector Signal Generator (Opt. 020)

Frequency Range: 125 MHz to 6 GHz

- Pre-installed Baseband Generator Vector Modulation Bandwidth: 120 MHz Sampling Clock: 20 kHz to 160 MHz
- Level Accuracy: ±0.5 dB
- Large-capacity Memory: 1 GB = 256 Msamples
- Internal AWGN Generator
- Internal BER Measurement Function Bit Rate: 100 bps to 10 Mbps Input Level: TTL
- *1: Difference between TOI and DANL as simple guide
- *2: TOI (Third Order Intercept)
- *3: DANL (Displayed Average Noise Level)
- *4: Spectrum Analyzer Functions
- *5: Signal Analyzer Functions
- *6: Use USB Power Sensors
- *7: Noise Figure Measurement Function (Requires Opt. 017) [Use Noise Sources (Noisecom, NC346 series)]
- *8: Requires MS269xA-077
- *9: Combining with MX269028A-002 wireless LAN IEEE 802.11ac (160 MHz) measurement software (only for MS269xA) supports modulation analysis up to 160-MHz bandwidth signals of the IEEE 802.11ac. See measurement software catalog for more details.
- *10: Opt. 067 can be installed in MS2692A



Panel Layout



- **1 Power switch:** Press to switch move between the standby state in which AC power is supplied and the Power On state in which the MS269xA in the operating mode.
- 2 Hard disk access lamp: Lights up when the MS269xA internal hard disk is being accessed.
- **3** Copy key: Press to capture a screen image from the display and save it to a file.
- 4 Recall key: Press to recall a parameter file.
- **5** Save key: Press to save a parameter file.
- 6 Cal key: Press to display the calibration execution menu.
- Cocal key: Press to return to local operation from remote control operation through GPIB, Ethernet or USB (B), and enable panel settings.
- **8 Remote lamp:** Lights up when the MS269xA is in a remote control state.
- **9 Preset key:** Resets parameters to their initial settings.
- Function keys: Used for selecting or executing function menu displayed on the right of the screen.
- Main function keys 1: Used to set or execute main functions of the MS269xA.
 Executable functions vary depending on the application currently selected.

- Main function keys 2: Used to set or execute main functions of the MS269xA.
 Executable functions vary depending on the application currently selected.
- (3) Rotary knob/Cursor key/Enter key/Cancel key: The rotary knob and cursor keys are used to select display items or change settings.
- Shift key: Used to operate any keys with functions described in blue characters on the panel. First press the Shift key, then press the target key when the Shift key lamp lights up green.
- 15 Numeric keypad: Used to enter numbers on parameter setup screens.
- 16 RF Input connector: Inputs an RF signal.
- **RF output control key:** If the MS269xA-020 Vector Signal Generator is installed, pressing enables (On) or disables (Off) the RF signal output. The lamp of the RF output control key lights up orange when the RF signal output is set to On.
- (B) RF output connector (when MS269xA-020 installed): Outputs an RF signal.
- USB connectors (type A): Used to connect a USB keyboard or mouse or the USB memory supplied with the MS269xA.





- Ref Input connector (reference frequency signal input connector): Inputs an external reference frequency signal (10 MHz/13 MHz). It is used for inputting reference frequency signals with accuracy higher than that of those inside the MS269xA, or for synchronizing the frequency of the MS269xA to that of another device.
- Buffer Out connector (reference frequency signal output connector): Outputs the reference frequency signal (10 MHz) generated inside the MS269xA. It is used for synchronizing the frequencies between other devices and the MS269xA based on the reference frequency signal output from this connector.
- Trigger Input connector: Inputs a trigger signal from an external device. Refer to the operation manual of each application for operations when a trigger signal is input.
- Sweep Status Out connector: Outputs a signal that is enabled when an internal measurement is performed or measurement data is obtained.
- IF Out connector: Outputs an IF signal. 874.988 MHz is specified as the center frequency during spectrum analyzer operations, and 875 or 900 MHz is specified during signal analyzer operations. (Bandwidth ≤31.25 MHz: 875 MHz, Bandwidth >31.25 MHz: 900 MHz) The IF signal is output without band limitation by RBW during both spectrum analyzer and signal analyzer operations.

- Aux connector: Composite connector for Vector Signal Generator options with Marker 1 to 3 outputs, pulse modulation input, baseband reference clock signal input, and BER measurement Clock, Data, and Enable inputs. Converted to BNC using optional AUX Conversion Adaptor (J1373A).
- GPIB connector: Used when controlling the MS269xA externally via GPIB.
- USB connector (type B): Used when controlling the MS269xA externally via USB.
- Ethernet connector: Used for connecting to a personal computer (PC) or for Ethernet connection.
- USB connectors (type A): Used to connect a USB keyboard or mouse or the USB memory supplied with the MS269xA.
- Monitor Out connector: Used for connection with an external display.
- 3 AC inlet: Used for supplying power.
- Noise Source Drive connector: This is available when the Option 017/117 is installed. Supply (+28 V) of the Noise Source Drive.

НАУЧНОЕ оборудование группа компания Product Brochure MS2690A/MS2691A/MS2692A 5

Excellent Total Level Accuracy: ±0.3 dB (typ.)

(Common to both Spectrum Analyzer and Signal Analyzer Functions)

With a 6-GHz basic band and level calibration over a wide frequency range, the MS269xA has excellent total level accuracy.

The Absolute Amplitude Accuracy specification described in catalogs of other spectrum analyzers ignores the important frequency characteristics, linearity, and attenuator switching errors. In contrast, the MS269xA Level Calibration technology assures excellent level accuracy over a wide frequency range from 50 Hz to 6 GHz even under measurement conditions including the above three errors. The level accuracy is assured even when the frequency and attenuator are switched.

Advantage of 6 GHz Basic Band

Conventional spectrum analyzers have a degraded noise floor above 3 GHz because they use a preselector at the 3-GHz basic band, which causes lowered measurement accuracy. The MS269xA basic band of 6 GHz eliminates the degraded noise floor and improves measurement accuracy.

Advantage of MS269xA Level Accuracy Technology

Conventional spectrum analyzers perform level calibration at just one frequency point, which causes errors when the frequency changes. The MS269xA has two built-in signal generators for level calibration over a wide frequency range from 50 Hz to 6 GHz, minimizing measurement errors in this frequency range.

The MS269xA total level accuracy includes:

- Frequency characteristics
- Linearity
- Attenuator switching error



Note: Eliminates effect of noise floor Used only when Uncal does not occur

*1: Excluding Guard Band



Preselector

The MS269xA has a basic band that goes to 6 GHz without a preselector. Most spectrum analyzers may use a preselector in the high band to clean-up images but it is extremely difficult to stabilize the amplitude and frequency characteristics of the preselector. This instability is the main cause of degraded level accuracy and modulation precision in measuring instruments.

Additionally, the preselector passband frequency can cause limitations at analysis bandwidths. No preselector means greater measurement accuracy.

MS2692A-067* Microwave Preselector Bypass

Bypasses the preselector to improve the RF frequency characteristics and the in-band frequency characteristics. When the preselector option is set to On, the image response elimination filter is bypassed. Therefore, this function is not appropriate for spurious

measurement to receive the image response.

*: Opt. 067 can be installed in MS2692A.



MS269xA Block Diagram

Example: Level Error Comparison with Different Level Calibration Method



The measuring instrument level error cannot be said to really meet the specifications if measurement requires addition of a margin to the product test specification. Since specifications with added margin are severe, even genuinely passing products may sometimes be evaluated as failing due to this margin.





Top Class Dynamic Range

Dynamic range^{*1}: 177 dB TOI^{*2}: ≥+22 dBm (700 MHz to 4 GHz) DANL^{*3}: −155 dBm/Hz (30 MHz to 2.4 GHz)

Dynamic range is a key specification for spectrum analyzers. Low displayed average noise level (DANL) as well as high TOI are important too.

Low TOI may cause distortion with high-level carrier signals. Inserting an attenuator can lower the carrier level but this has the effect of lowering the level of weak spurious, making it hard to measure.

- *1: Difference between TOI and DANL as simple guide.
- *2: TOI (Third Order Intercept)
- *3: DANL (Displayed Average Noise Level)

The MS269xA has an excellent dynamic range supporting true performance measurements of devices, such as base stations, requiring wideband measuring instruments.

For example, the 3GPP category-B spurious measurement specification requires a measuring instrument with severe dynamic range specifications. If the measurement is within the MS269xA dynamic range, measurement jigs such as filters and amplifiers are unnecessary and troublesome calibration is omitted, helping simplify setup and cut costs.





Example: SSB Phase Noise (Spectrum Analyzer/Signal Analyzer Common)





Supports 125 MHz Wideband Measurements up to 26.5 GHz

MS2692A-067 Microwave Preselector Bypass^{*1} + MS2692A-078 Analysis Bandwidth Extension to 125 MHz^{*2}

*1: Can be installed in MS2692A.

*2: Require MS2692A-077.

Supports wideband analysis with high frequencies for satellite communications

Microwave preselector bypass frequency range: 6 GHz to 26.5 GHz (MS2692A)

Installing the microwave preselector bypass supports signal analyzer measurement functions in the above frequency range.



Provided by customer



Improved Level Linearity

Conventional spectrum analyzers use an analog IF and log amp to achieve good level accuracy at points near the log scale reference level, but the accuracy degrades at points that are further away. The MS269xA uses a digital IF instead of a log amp, which supports measurements with excellent accuracy at any point.

Example: Level Stability by Switching Reference Level







Level Linearity:

The MS269xA total level accuracy is better than that of conventional spectrum analyzers but sometimes a power meter is used when wanting to measure with even higher accuracy. However, use of a power meter narrows the dynamic range and errors may also occur easily when switching the power range. Since a power meter has no frequency selection, the total power of the input signal is measured. In other words, the power of the target frequency components cannot be separated out.

Measurement can be performed with a wide dynamic range after checking the MS269xA level measurement reference value with a power meter.

The MS269xA total level accuracy includes:

- Frequency characteristics
- Linearity
- Attenuator switching error
- And supports excellent:
- Log scale stability

Dual Sweep Speed: Normal/Fast

When sweep time is set to [Auto], Normal (normal sweep) or Fast mode (high-speed sweep) can be set. The Fast mode sweeps six times faster than the Normal mode.

Example of Sweep Mode Switch Error: (CW –10 dBm input) Level Error when Switching from Normal to Fast





Resolution Bandwidth (RBW)

Setting Range (Spectrum Analyzer): 30 Hz to 3 MHz (1-3 sequence), 50 kHz, 5 MHz, 10 MHz, 20 MHz, 31.25 MHz^{*1} Setting Range (Spectrum trace in signal analyzer mode): 1 Hz to 1 MHz (1-3 sequence), 3 MHz^{*2, *3}, 10 MHz^{*3}

When monitoring two adjacent signals, the frequency resolution can be increased by reducing the resolution bandwidth (RBW). This also has the effect of reducing the noise level. Conversely, to confirm level variations of 20-MHz band signals such as LTE and WiMAX, set the RBW to 31.25 MHz.

- *1: Instead of Gaussian filter, 31.25 MHz RBW uses filter with flat top characteristics above 31.25 MHz.
- *2: With Opt. 077 installed and bandwidth setting ≥50 MHz
- *3: With Opt. 077+078 installed and bandwidth setting ≥50 MHz

Trigger Function

Trigger sweep executes sweeping using the specified trigger condition as the start point. In particular, "SG Marker" starts analyzer measurement in synchrony with the signal output by installing Opt. 020. Using this function supports simple synchronized measurement even when evaluating signals with large level variation over time, such as modulation signals.

• Video trigger:

Trigger sweeping starts in synchronization with the rise or fall of the waveform. A trigger level indicator showing the trigger level is displayed on the screen.

- Wide IF video trigger: An IF signal with a wide passing band of about 50 MHz is detected, and sweeping starts in synchronization with either the rise or fall of the detected signal.
- External trigger: Sweeping starts in synchronization with the rise or fall of the signal input via the Trigger Input connector.

 SG Marker trigger (Requires Opt. 020): Sweeping starts in synchronization with the rise or fall of the marker signal output of Opt. 020. This function supports measurement in synchronization with the output signal of Opt. 020.

Gate Sweep

Gate sweep executes sweeping only for the length of time specified by the gate length, starting from when the trigger condition is met. A delay time until sweeping starts after the trigger condition is met can be set using trigger delay.

- · The gate source can be selected from the following
 - Wide IF video trigger
 - External trigger
- SG marker trigger (Requires Opt. 020)
- Setting range and resolution for gate delay
 - Setting range: 0 to 1 s
 Resolution: 20 ns
- Setting range and resolution for gate length
 - Setting range: 50 µs to 1 s
 - Resolution: 20 ns

Three Built-in External Interfaces

The built-in Gigabit Ethernet, USB2.0, and GPIB interfaces support remote operation.

GPIB: IEEE 488.2, Rear panel, IEEE 488 bus connector Interface functions: SH1, AH1, T6, L4, SR1, RL1, PP0, DC1, DT0, C0, E2

Ethernet: 10/100/1000BASE-T, Rear panel, RJ-45 USB (B): USB2.0, Rear panel, USB-B connector

Saving Measurement Results

Measurement results can be saved to internal hard disk or external USB memory. Screen dumps and trace data can be saved too.

- Screen dump file type
 - BMP - PNG
 - NG
- The color of the screen hard copy can be set as follows:
 Normal (same as screen display)
 - Reverse
 - Monochrome
 - Reversed Monochrome



Signal Analyzer: Basic Performance/Functions

Wide bandwidth × High Accuracy FFT Analysis

Standard: 31.25 MHz max.

(Sampling rate 50 MHz max = Resolution 20 ns, ADC resolution 16 bits)

Opt. 077: 62.5 MHz max.

(Sampling rate 100 MHz max = Resolution 10 ns, ADC resolution 14 bits)

Opt. 078*1, *2: 125 MHz max.

(Sampling rate 200 MHz max = Resolution 5 ns, ADC resolution 14 bits)

Based on the excellent level accuracy and wide dynamic range of the MS269xA, a signal with an FFT analysis bandwidth of up to 125 MHz can be captured with a level accuracy of ± 0.3 dB.



- *1: Requires Opt. 077
- *2: Combining with MX269028A-002 wireless LAN IEEE 802.11ac (160 MHz) measurement software (only for MS269xA) supports modulation analysis up to 160-MHz bandwidth signals of the IEEE 802.11ac. See measurement software catalog for more details.
- *3: 50 Hz \leq Frequency \leq 6.0 GHz, Frequency band mode: Normal

*4: Excluding Guard Band

Excellent Frequency Characteristics in Analysis Bandwidth

The Signal Analyzer Extra Band Cal function using the built-in oscillator for calibration supports analysis bandwidth calibration at the set frequency.

The excellent in-band frequency characteristics support wideband modulation analysis with less error.

Extra Band Cal Frequency Range

Span ≤ 31.25 MHz (Standard): 30 MHz to 6 GHz Span > 31.25 MHz (Opt. 077/078): 100 MHz to 6 GHz

*: Setting center frequency after Extra Band Cal, requires re-execution of Extra Band Cal.

Example of frequency characteristics in analysis bandwidth after Extra Band Cal

(With Opt. 078, Reference Level: -10 dBm, Input attenuator: 10 dB, Preamp: Off, Span: 125 MHz)



Save Signals in Internal Memory

Max. Capture Time: 0.5 s to 2000 s Max. Number of Samples: 100 Msamples

The "Analysis bandwidth × Analysis time" signal is held in internal memory and saved to hard disk.

Up to 100 Msamples of data can be saved to memory for one measurement. The frequency span determines the sampling rate. The following chart shows the maximum capture time per frequency span.

Span	Sampling Rate	e Capture Time	Max.
			Sampling Data
1 kHz	2 kHz	2000 s	4M
2.5 kHz	5 kHz	2000 s	10M
5 kHz	10 kHz	2000 s	20M
10 kHz	20 kHz	2000 s	40M
25 kHz	50 kHz	2000 s	100M
50 kHz	100 kHz	1000 s	100M
100 kHz	200 kHz	500 s	100M
250 kHz	500 kHz	200 s	100M
500 kHz	1 MHz	100 s	100M
1 MHz	2 MHz	50 s	100M
2.5 MHz	5 MHz	20 s	100M
5 MHz	10 MHz	10 s	100M
10 MHz	20 MHz	5 s	100M
25 MHz	50 MHz	2 s	100M
31.25 MHz	50 MHz	2 s	100M
50 MHz*	100 MHz	500 ms	50M
62.5 MHz*	100 MHz	500 ms	50M
100 MHz*	200 MHz	500 ms	100M
125 MHz*	200 MHz	500 ms	100M

*: With MS269xA-077: 50/62.5 MHz

With MS269xA-077/078: 50/62.5/100/125 MHz

Replay Function for Comparison Evaluation

This function reads saved data and replays it using the signal analyzer measurement function.

Examples:

- 1. Data sharing between separate R&D and manufacturing
- 2. Later laboratory bench-top analysis of on-site signals
- 3. Save data at shipment and re-verify if problem occurs

Captured Waveform Data: Selection Screen





Signal Analyzer: Trace

Spectrum

The Spectrum trace displays a graph with amplitude on the y-axis and frequency on the x-axis. The captured IQ data is FFT processed (fast Fourier transformed) and converted from the time domain to the frequency domain for display as a spectrum.



Power vs. Time

The Power vs. Time trace displays a graph with amplitude on the y-axis and time on the x-axis to confirm changes in power with time of measured signals.



Frequency vs. Time

The Frequency vs. Time trace displays a graph with frequency on the y-axis and time on the x-axis to confirm time variation of the measured signal frequency.



Phase vs. Time

The Phase vs. Time trace displays a graph with phase on the y-axis and time on the x-axis to confirm time variation of the measured signal phase.



CCDF*1/APD*2

The CCDF trace displays the power variation probability on the y-axis and power variation on the y-axis to confirm the CCDF and APD of measured signals.

*1: CCDF (Complementary Cumulative Distribution Function) *2: APD (Amplitude Probability Density)



Measurement Results

- CCDF: The CCDF display indicates the cumulative distribution of transient power variations compared to average power.
- APD: The APD display indicates the probability distribution of transient power fluctuations compared to average power.



Signal Analyzer: Trace

Spectrogram

The Spectrogram trace displays the level as color with frequency on the y-axis and time on the x-axis. The captured IQ data is FFT processed to confirm time variations in the continuous spectrum. It is useful for monitoring frequency hopping and transient signals.



No Trace

No Trace mode does not execute signal analysis. Therefore, "IQ data output" and "IQ data readout using remote commands" can be executed quickly without the need to wait for completion of analysis.

Mo Trans			_		Contract Bankara
NO Trace		Analysis Start Ti	-	0 =	Dearer
		Analysis Time Le	ingth	100.000 00 ms	Trace Mode
Only capturing IQ data to the v Captured data can be read out	eveform men by query con	ory mand and saved int	oa file.		Analysis Time
mmon					
requency and Time	Level		Trigger-		
Center Freq. 6.000 000 000 GHz Freq. Span 31.25 MHz	Ref, Level	0.00 dBm	Trigger	Free Run	

Measurement with Sub-trace Display

This function splits the screen into top and bottom halves; simultaneous display of the sub-trace supports easy monitoring of fault locations and transient phenomena.

Main: Spectrum, Frequency vs. Time, Power vs. Time, Phase vs. Time, CCDF/APD, Spectrogram Sub: Power vs. Time, Spectrogram

The part of a previously captured long-term signal to be monitored can be selected (Blue part) on the sub-trace to display the problem part only on the main trace.





Signal Analyzer: Trace

Example: Sub-trace Display

Confirm analysis range in sub-trace, and target signal status on main trace.





Signal Analyzer: Applications

Analyze Captured Waveforms using Third-Party Tools

The MS269xA utilizes proprietary calibration technologies, enabling digitized baseband data to be used directly in third-party analysis tools without the need for correction.

Capture & Playback Real-World Signals

The MS269xA provides *Capture & Playback* functionality that enables laboratory-grade testing of transceiver systems using real world signals. Using the optional integrated Vector Signal Analyzer and Vector Signal Generator of the MS269xA, *Capture & Playback* allows users to conveniently capture up to 100 MHz of spectrum and play it back at any designated frequency and amplitude, making it easy to determine device performance margins.

Applications for Capture & Playback

Validation/Production Test

Captured signals can be used to initiate a communications link and perform receiver sensitivity testing with a device under test (DUT) using signals captured from a Golden Unit.

Device Characterization

Actual baseband signals captured from an RFIC can be used as simulation for characterizing amplifiers and other downstream devices or modules.

Electromagnetic Compatibility Test

Problematic RF environments or discrete signals – such as cellular or Wi-Fi – can be captured and used to evaluate a device's susceptibility to RF interference, debug any problems found and validate the solution





Repeatably Test Device Performance using "Real-World" RF Environments



Use "Golden Unit" Signal for Manufacturing Test and Calibration



Signal Analyzer: Applications

Capture & Playback Highlights

- Bandwidth and Time Limits
 - Minimum 10 kHz Bandwidth (2000 s maximum duration)* Maximum 100 MHz Bandwidth (500 ms maximum duration)*
 - *: Maximum bandwidth depends upon vector signal analyzer options installed (Standard analysis bandwidth or Opt. 077/078).
- Captured signal may be freely tuned to any output frequency and amplitude supported by the vector signal generator.
- Any section of the captured waveform record may be selected and played back.
 - \checkmark Enables user to isolate and reproduce specific signal bursts
 - ✓ Enables user to change duty cycle of pulsed waveforms



Playback Block Diagram



Playback any Desired Section of Captured Waveform



Useful for Tx Characteristics Evaluation

The MS269xA is fully loaded with all the functions required for evaluating Tx characteristics. Tests can be performed simply and in accordance with standards using functions tailored to measurement contents.

Measure Function	SPA*1	VSA*2	
Channel Power	✓	~	
Occupied Bandwidth	✓	~	
Adjacent Channel Leakage Power	✓	~	
Spectrum Emission Mask	✓		
Burst Average Power	✓	~	
Spurious Emission	✓		
AM Depth		~	
FM Deviation		~	
Multi-marker & Marker List	✓	✓	
Highest 10 Markers	✓	~	
Limit Line	✓		
Frequency Counter	✓		
2-tone 3rd-order Intermodulation Distortion	✓		
Annotation Display (On/Off)	✓		
Phase Noise	Independe	ent function	
Power Meter	Independent function*3		
Noise Figure	Opt. 017*4		

*1: SPA (Spectrum Analyzer)

*2: VSA (Vector Signal Analyzer)

*3: Use USB Power Sensors

*4: Use Noise Sources (Noisecom, NC346 series)

Channel Power

SPA VSA

This function measures channel bandwidth power. Three types of filters (Rect, Nyquist, Root Nyquist) can be selected. Pre-installed templates for each standard support easy parameter setting.



Measurement Results

- Absolute power per Hz in channel band
- Total power in channel band

Occupied Bandwidth

(SPA) (VSA)

Occupied bandwidth is measured by selecting either the N% or X-dB mode.

Pre-installed templates for each standard support easy parameter setting.

Measurement Results

Bandwidth for specified conditions

Adjacent Channel Leakage Power SPA VSA

This function measures carrier adjacent channel (offset) power (In-Band).

1 to 12 carriers can be set and switched instantaneously on-screen. True ACLR performance is measured using the noise cancellation function to subtract main-frame noise from the measurement result. Pre-installed templates for each standard support easy parameter setting.

Measurement Results

- Absolute power of Offset channel
- Relative values in relation to reference power selected in ACP reference

Spectrum Emission Mask

This function splits the offset part into up to 12 segments; the measurement parameters and limit lines can be specified to measure the peak power and margin for each segment. The results are tabulated below the trace and marked PASS/FAIL. Pre-installed templates for each standard support easy parameter setting.

Measurement Results

- Peak power (or margin) at offset
- Each peak frequency

Burst Average Power

(SPA) (VSA)

(SPA)

The average power for the range specified by two markers is displayed in the time domain. Measurement only requires setting the measurement start and stop positions on the screen. True performance is measured using the noise cancellation function to subtract main-frame noise from the measurement result. Preinstalled templates for each standard support easy parameter setting.

Measurement Results

Average power of specified range

Spurious Emission

This function splits the frequency range into up to 20 segments for sweeping; the measurement parameters and limit lines can be specified to measure the peak power and margin for each segment. The results are tabulated below the trace and marked PASS/FAIL. In particular, all tests can be completed up to the final stage without an external PC because the zero-span capture function described in the technology compliance test is built-in.

SPA

Measurement Results

- Each segment peak power and margin
- Each peak frequency

Example: Spurious Emission

The Japanese Radio Law governing measurement of spurious specifies searching for the peak level in the swept frequency segment using different parameter settings and then performing zero-span measurement of the found peak point. The MS269xA spurious measurement function not only performs the sweep search but also performs the zero-span measurement automatically as well, and displays the results of both. Using zero-span measurement, the search screen is displayed as is while zero-span measurement runs in the background and the result markers are plotted on the search screen. Time wasted by screen switching is reduced and the correlation with the search results can be seen at a glance.

Measurement Example

Search + Measurement

AM Depth

(VSA)

The Power vs. Time trace measurement function is used to confirm AM depth.

It measures the measured signal AM based on trace data at the displayed marker. When marker is Off, the whole range is measured.

Measurement Results

■ +Peak, -Peak, (Peak-Peak)/2, Average

FM Deviation

The Frequency vs. Time trace measurement is used to confirm the FM deviation. It measures the maximum and minimum frequencies from trace data in the marker range. When marker is Off, the whole range is measured.

Measurement Results

+Peak, -Peak, (Peak-Peak)/2, Average

Multi-marker & Marker List

Up to 10 markers can be set for this function. Markers may be either a spot or a zone. Using a zone marker, the peak of a signal with an unstable variable frequency can be tracked and measured. Not only can the 10 markers be listed below the trace but the differences between markers can be calculated and displayed using the delta setting.

Measurement Results

- Marker point frequency
- Marker point power
- Absolute power per Hz in marker bandwidth
- Total power in marker bandwidth
- Difference between any markers

Highest 10 Markers

SPA VSA

(SPA)

(VSA)

This function sets the threshold level and auto-detects peaks in the X (frequency) and Y (level/time) directions.

Measurement Results

- Peak Search Y:
- Sets up to 10 markers in order of peak level
- Peak Search X:
 - Sets up to 10 markers in order of frequency (time) level

Limit Lines

Setting Limit Lines

Up to six types of Limit line can be set on the spectrum display (frequency domain).

In addition to setting the frequency and level of crossover points manually in sequence from the low frequency, after creating the right half of a line, the left half can be created by reversing and copying the right half, to set a symmetric limit line. Additionally, a Limit line that traces the measured waveform can be created using the Limit Envelope function. A margin can be set on the Limit line in the amplitude direction.

Evaluating using Limit Line Setting (Limit Test Function)

When the waveform is above or below the Limit line, it is evaluated automatically as PASS or FAIL. Evaluation is also possible with an added margin. The target evaluation line can be chosen from any of six types.

Auto-saving Waveform Data using Limit Line Setting (Save on Event Function)

When the waveform matches the evaluation conditions (Event), it can be saved automatically as a csv format file. Any one of the following five Event types can be selected.

- (1) Limit Fail: Saves waveform file when evaluation result is Fail
- (2) Limit Pass: Saves waveform file when evaluation result is Pass
 (3) Margin Fail: Saves waveform file when evaluation result including margin is Fail
- (4) Margin Pass: Saves waveform file when evaluation result including margin is Pass
- (5) Sweep Complete: Saves waveform file at every measurement regardless of evaluation result

Example:

PASS/FAIL evaluation is performed by changing the input signal level.

The evaluation results for the five line types can be displayed simultaneously on one screen.

Line: Limit 1, Limit 2, Limit 3, Limit 4, Limit 5, Limit 6 Evaluation Type: Upper Limit, Lower Limit Crossover (Point): 1 to 100 Margin: Set Margin line for each Limit 1, 2, 3, 4, 5, 6 Evaluation Result: PASS, FAIL Result Save: Auto-save as csv format file

Frequency Counter

(SPA)

This function of the marker functions is used to measure CW frequencies.

Gate Time sets the measurement target time.

Measurement Results

Marker point frequency

2-tone 3rd-order Intermodulation Distortion

SPA

(SPA)

By inputting two different frequency CW signals (desired waves), two-tone third-order intermodulation distortion is generated close to the desired waves according to non-linear characteristics of Device Under Test (DUT). Then, Third Order Intercept (TOI) is calculated from the two-tone third-order intermodulation distortion.

Measurement Results

- TOI: [dBm]
- Amplitude: [dBc]

Annotation Display

(SPA)

Screen annotations can be set to On or Off. Annotations about frequency, level, etc., are not displayed at the Off setting.

Phase Noise

This function measures phase noise in the 10 Hz to 10 \mbox{MHz} frequency offset range.

Measurement Results

- Carrier level
- Error between set frequency and carrier frequency
- Marker point phase noise level

Power Meter

Power meter function can connect a USB power sensor to the MS2830A and read the measurement values.

Measurement Results

- Power: [dBm], [W]
- Relative power: [dB]

Compatible USB power sensors.

Model	Frequency Range	Resolution	Dynamic Range
MA24104A*	600 MHz to 4 GHz	1 kHz	+3 to +51.76 dBm
MA24106A	50 MHz to 6 GHz	1 kHz	-40 to +23 dBm
MA24108A	10 MHz to 8 GHz	100 kHz	-40 to +20 dBm
MA24118A	10 MHz to 18 GHz	100 kHz	-40 to +20 dBm
MA24126A	10 MHz to 26 GHz	100 kHz	-40 to +20 dBm

*: MA24104A has been discontinued.

Noise Figure Measurement (Opt. 017)

Noise Figure is measured with the measurement method of Y-factor method which uses a Noise Source.

Frequency Mode: Fixed/List/Sweep DUT Mode: Amplifier Screen Layout: Graph/Table

Measurement Results Display

Graph/List/Spot

Displays measurement results for each trace (Trace1/Trace2).

- Noise Figure (NF) [dB]
- Noise Factor (F) [Linear]
- Gain
- Y-Factor: Power ratio when Noise Source is turned ON/OFF
- T effective: Effective noise temperature
- P Hot: Power measured when Noise Source is On.
- P Cold: Power measured when Noise Source is Off.

Measurement Result: Example of Graph display (Frequency Mode: Sweep, Screen Layout: Graph)

Measurement Result: Example of List display (Frequency Mode: List, Screen Layout: List)

v .	000 000Hz	ATT	A-00	0dB	Loss Status	Befare:0f	P None Farm Trace	
		T cold	296	50K	CAL Status	OIK	Truce Selec	
suff (INR Status Average	Teble 10 4 10	1 2	
Fre	quency		Noise Figure		Gain		Result Type Noise Figure	
1 000 00	00 000H	z	2.09268dB	1	4.554700	B		
Noise Figure							_	
Noise Figure								
			NEM	ax	2.120	25dB		
NF Current	2.0828	37dB	NF N	lin	2.062	44dB		
NF Average	2.0926	68dB	NF Max to N	lin	0.057	81dB		
							Reference	
							3 004B	
							Scale/Div	
							1 000 100	

Measurement Result: Example of Spot display (Frequency Mode: Fixed)

Noise Source

Supports noise sources from Noisecom NC346 series. NC346 series models and summary specifications are listed below. See the NC346 series catalog and datasheet for detailed specifications.

Madal	RE Connector Freque		RE Connector Frequency Output ENR			VSWR (maximum @ on/off) [GHz]				DC Offeet	DC Blook
IVIOUEI	KF Connector	[ĠHz]	[dB]	0.01 to 5	5 to 18	18 to 26.5	26.5 to 40	DC Oliset	DC BIOCK		
NC346A	SMA (M)	0.01 to 18.0	5 to 7	1.15:1	1.25:1	—	—	No	Not required		
NC346A Precision	APC3.5 (M)	0.01 to 18.0	5 to 7	1.15:1	1.25:1	—	—	No	Not required		
NC346A Option 1	N (M)	0.01 to 18.0	5 to 7	1.15:1	1.25:1	—	—	No	Not required		
NC346A Option 2	APC7	0.01 to 18.0	5 to 7	1.15:1	1.25:1	—	—	No	Not required		
NC346A Option 4	N (F)	0.01 to 18.0	5 to 7	1.15:1	1.25:1	—	—	No	Not required		
NC346B	SMA (M)	0.01 to 18.0	14 to 16	1.15:1	1.25:1	—	—	No	Not required		
NC346B Precision	APC3.5 (M)	0.01 to 18.0	14 to 16	1.15:1	1.25:1	—	—	No	Not required		
NC346B Option 1	N (M)	0.01 to 18.0	14 to 16	1.15:1	1.35:1	—	—	No	Not required		
NC346B Option 2	APC7	0.01 to 18.0	14 to 16	1.15:1	1.25:1	—	—	No	Not required		
NC346B Option 4	N (F)	0.01 to 18.0	14 to 16	1.15:1	1.35:1	—	—	No	Not required		
NC346D	SMA (M)	0.01 to 18.0	19 to 25*1	1.50:1	1.50:1	—	—	No	Not required		
NC346D Precision	APC3.5 (M)	0.01 to 18.0	19 to 25*1	1.50:1	1.50:1	—	—	No	Not required		
NC346D Option 1	N (M)	0.01 to 18.0	19 to 25*1	1.50:1	1.75:1	—	—	No	Not required		
NC346D Option 2	APC7	0.01 to 18.0	19 to 25*1	1.50:1	1.50:1	—	—	No	Not required		
NC346D Option 3	N (F)	0.01 to 18.0	19 to 25*1	1.50:1	1.75:1	—	—	No	Not required		
NC346C	APC3.5 (M)	0.01 to 26.5	13 to 17	1.15:1	1.25:1	1.35:1	—	Yes ^{*3}	Required ^{*3}		
NC346E	APC3.5 (M)	0.01 to 26.5	19 to 25*1	1.50:1	1.50:1	1.50:1	_	Yes ^{*3}	Required ^{*3}		
NC346Ka	K (M)*2	0.10 to 40.0	10 to 17	1.25:1	1.30:1	1.40:1	1.50:1	Yes*3	Required ^{*3}		

NC346 series summary specifications

*1: Flatness better than ±2 dB

*2: Compatible with SMA and APC3.5

*3: When using noise sources output by DC, always use in combination with a DC block.

Specifications outlines of recommended DC Blocks and Adapters

		Model	Ordering Name	RF Connector	Frequency Range	VSWR
		J0805	DC Block, N type (MODEL 7003)	N (M)-N (F)	10 kHz to 18 GHz	1.35 (max.)
	J1555A	DC Block, SMA type (MODEL 7006-1)	SMA (M)-SMA (F)	9 kHz to 20 GHz	1.50 (9 kHz to 10 kHz) 1.50 (11 kHz to 20 kHz) 1.30 (20 kHz to 20 GHz)	
	DC Block	J1554A	DC Block, SMA type (MODEL 7006)	SMA (M)-SMA (F)	9 kHz to 26.5 GHz	1.50 (9 kHz to 20 kHz) 1.35 (20 kHz to 20 GHz) 1.70 (20 GHz to 26.5 GHz)
		K261	DC Block	K (M)-K (F)	10 kHz to 40 GHz	See figure (return loss) below
		J0004	Coaxial Adapter	N (M)-SMA (F)	DC to 12.4 GHz	≤1.08 (DC to 3 GHz) ≤1.11 (3 GHz to 6 GHz) ≤1.18 (6 GHz to 12.4 GHz)
	Adapter	J1398A	N-SMA Adapter	N (M)-SMA (F)	DC to 26.5 GHz	≤1.05 (DC to 3 GHz) ≤1.07 (3 GHz to 6 GHz) ≤1.2 (6 GHz to 13.5 GHz) ≤1.3 (13.5 GHz to 20 GHz) ≤1.45 (0 GHz to 20 GHz)

Typical Low Frequency Insertion Loss measured on K261 over the range of 1 kHz to 1 MHz.

Loss measured Insertion Loss and Return Loss measured on K261 over the range of 40 MHz to 40 GHz. **K261 DC Block Return Loss**

Recommended DC blocks / Adaptor combinations for MS269xA/MS2830A series signal analyzer

	Model	Frequency Range	RF connector	Recommended DC Block Order Name	Recommended Adapter Order Name
	MS2690A	50 Hz to 6 GHz	N (F)	J1555A	J0004
MS269xA series	MS2691A	50 Hz to 13.5 GHz	N (F)	J1555A	J1398A
	MS2692A	50 Hz to 26.5 GHz	N (F)	J1554A	J1398A
	MS2830A-040	9 kHz to 3.6 GHz	N (F)	Not required	Not required
	MS2830A-041	9 kHz to 6 GHz	N (F)	Not required	Not required
MS2830A	MS2830A-043	9 kHz to 13.5 GHz	N (F)	Not required	Not required
301103	MS2830A-044	9 kHz to 26.5 GHz	N (F)	J1554A	J1398A
	MS2830A-045	9 kHz to 43 GHz	K (F)	K261	Not required

24 Product Brochure MS2690A/MS2691A/MS2692A

НАУЧНОЕ ОБОРУДОВАНИЕ группа компаний

Vector Signal Generator (Opt. 020): Basic Performance

The MS269xA-020 Vector Signal Generator option covers the frequency range from 125 MHz to 6 GHz; it has a wide vector modulation bandwidth of 120 MHz as well as a large built-in memory for storing 256 Msamples. Its level accuracy is at least as good as a dedicated signal generator and the ACLR performance is ideal for Tx tests of devices such as amplifiers and Rx tests of base stations. The all-in-one analyzer and signal generator supports simple configuration of space-saving measurement systems as well as a seasy signal analysis matching the output timing from the signal generator option.

Frequency Range

Frequency Range: 125 MHz to 6 GHz Resolution: 0.01 Hz step

The Vector Signal Generator (Opt. 020) frequency range is 125 MHz to 6 GHz, covering the key wireless communication range.

Internal Baseband Generator

Vector Modulation Bandwidth: 120 MHz Sampling Clock: 20 kHz to 160 MHz

The wideband 120-MHz vector modulation bandwidth is achieved using the Opt. 020 baseband signal generator. The sampling clock supports up to 160 MHz.

Example: Vector Modulation Bandwidth

Level Accuracy ±0.5 dB

Output Level Accuracy (CW):

±0.5 dB (–120 dBm ≤ Level ≤ +5 dBm, Frequency ≤3 GHz) ±0.8 dB (–110 dBm ≤ Level ≤ +5 dBm, Frequency >3 GHz)

Example: Frequency Characteristics (Referenced to –5 dBm)

Example: SSB Phase Noise

Vector Signal Generator (Opt. 020): Basic Performance

Large-capacity Memory

1GB = 256 Msamples/channel

The MS269xA-020 arbitrary waveform memory can save 256 Msamples/ channel as well as multiple waveform patterns at the same time. Waveform patterns in memory can be output instantaneously by switching without need to recall from hard disk.

Internal AWGN Generator

Absolute CN Ratio: ≤40 dB

This functions adds AWGN (Additive White Gaussian Noise) to the wanted waveform in memory. It is ideal for Tx dynamic range tests.

AWGN band set automatically to sampling clock of wanted signal.

Example: When wanted signal conditions are:

- W-CDMA
- Bandwidth = 3.84 MHz
- Over sampling = × 4

Wanted Signal + AWGN Signal output from one unit

Versatile Multiple Waveform Generation

Any type of waveform can be generated using the MS269xA-020 Signal Generator option. In addition to using C and simulation tools, Anritsu's IQproducer can be run on a PC to edit waveform parameters and output waveforms.

Internal BER Measurement Function

Input Bit Rate: 100 bps to 10 Mbps Input Level: TTL Level Input Signal: Data, Clock, Enable Connector: Rear panel, Aux connector^{*}

*: Requires J1373A AUX Conversion Adapter (sold separately)

Adding the MS269xA-020 Vector Signal Generator option includes a built-in BER tester for measurements up to 10 Mbps. It supports Rx sensitivity tests by inputting the receiver-demodulated Data/ Clock/Enable to the back of the MS269xA.

					and ten
Data Type Pre Pattern File Bit Length		Count M Data Error	ode Da	1000 Bit Bit	Measure
Sync Position St Sync Position Le Measure Mode	irt				Mossure Stop
Measure Information Status Error SyncLoss Count	I Stop Synchronizir BitError SyncLes 0	ng Measuring Is ClockError	EnableEr	for	CoottOka
Error Rate	0.000)E+000		0.000%	Data Type PND
Error Cour	nt	0		0	Measure Mo

Creating Waveform Using IQproducer

IQproducer is PC software that is used to edit parameters and create any waveform pattern. It can be installed either on an external PC or in the MS269xA main frame.

- HSDPA/HSUPA IQproducer
- TDMA IQproducer
- Multi-carrier IQproducer
- Mobile WiMAX IQproducer
- LTE IQproducer
- LTE TDD IQproducer
- WLAN IQproducer
- TD-SCDMA IQproducer

Creating Any Waveform

IQ Data created using the MS269xA digitize function or by simulation tools or in C can be converted to a waveform pattern using the SG option and output.

Vector Signal Generator (Opt. 020): Basic Performance

Useful IQproducer Waveform Generation Software

IQproducer is application software for a PC for editing, creating and transferring waveform patterns using the MS269xA-020 arbitrary waveform generation option.

It has the following three main functions.

Parameter Editing:

Function for easily editing parameters matching each communication method

Simulation:

Function for checking generated waveform pattern before transfer to CCDF and FFT graphs

Conversion:

Function for converting ASCII format waveform patterns created by simulation software, files captured using digitizing function, and MG3700A waveform patterns, into files that can be used by MS269xA-020

Parameter Setting Screen (HSDPA/HSUPA IQproducer)

Convert Screen

Application

Excellent Expandability Platform (Hardware)

The versatility of the MS269xA series is tailored easily to the application by installing modules in expansion slots.

Basic Function and Performance Upgrades

MS2690A/MS2691A/MS2692A-001

Rubidium Reference Oscillator

This option is a 10 MHz reference crystal oscillator with excellent frequency stability startup characteristics of $\pm 1 \times 10^{-9}$ at 7 minutes after power-on.

Aging Rate: $\pm 1 \times 10^{-10}$ /month

Start-up Characteristics: $\pm 1 \times 10^{-9}$ (7 minutes after power-on)

MS2691A/MS2692A-003

Preselector Extended Lower Limit (3 GHz)

This option extends the lower limit of the preselector from 5.9 GHz to 3 GHz. It can only be installed in the MS2691A/MS2692A.

MS2690A/MS2691A/MS2692A-008

6 GHz Preamplifier

This option increases the sensitivity of the spectrum/signal analyzer functions and is used for examining low-level signals such as interference waveforms.

Frequency Range: 100 kHz to 6 GHz

Gain: 14 dB (≤3 GHz)

13 dB (3 GHz < Frequency \leq 4 GHz) 11 dB (4 GHz < Frequency \leq 5 GHz) 10 dB (5 GHz < Frequency \leq 6 GHz)

MS2692A-067 Microwave Preselector Bypass

Bypassing the preselector used for the microwave band improves RF frequency characteristics and in-band frequency characteristics.

*: Cannot be installed simultaneously with MS2692A-003/008

Signal Analyzer Function and Performance Upgrade

MS2690A/MS2691A/MS2692A-077

Analysis Bandwidth Extension to 62.5 MHz This option expands the analysis bandwidth to 62.5 MHz.

MS2690A/MS2691A/MS2692A-078*1,*2 Analysis Bandwidth Extension to 125 MHz

This option expands the analysis bandwidth to 125 MHz.

*1: Requires Opt. 077

*2: Combining with MX269028A-002 wireless LAN IEEE 802.11ac (160 MHz) measurement software (only for MS269xA) supports modulation analysis up to 160-MHz bandwidth signals of the IEEE 802.11ac. See measurement software catalog for more details

Usage Example: Record Noise and Replay

When the Vector Signal Generator (Opt. 020) generates a signal based on the data captured by the signal analyzer, a signal that mimics the captured signal can be output^{*1}. The Capture & Playback function can also be used for capture and replay using a simple procedure.

For example, a variety of noise sources can be captured and edited using one MS269xA to evaluate the noise tolerance of a product. In some cases, it is not possible to capture minute level fluctuations with a resolution of 20 ns^{*2}, depending on the noise components. In these circumstances, a signal very close to the actual noise can be captured and replayed by setting the resolution to 5 ns^{*3}.

(At signal generation, the setting range of the pattern sampling rate must be within the 160 MHz upper limit of the vector signal generator sampling rate.)

- *1: Capture time depends on memory capacity.
- *2: Sampling rate of 50 MHz at 31.25 MHz FFT band
- *3: Sampling rate of 200 MHz at 125 MHz FFT band

Expansion Functions

MS2690A/MS2691A/MS2692A-017

Noise Figure Measurement Function Adds noise figure measurement function. Noise Figure is measured with the measurement method of

Y-factor method which uses a Noise Source.

MS2690A/MS2691A/MS2692A-020 Vector Signal Generator

This option is a high-performance waveform generator covering a frequency range of 125 MHz to 6 GHz with a 120 MHz wideband vector modulation band and built-in 256 Msample waveform memory.

MS2690A/MS2691A/MS2692A-050 HDD Digitizing Interface

Installing the MS269xA-050 HDD Digitizing Interface option captures up to 4 hours of 20 MHz wideband RF signals. It is convenient for troubleshooting uncommon faults.

External HDD (≥1 TB)

MS2690A/MS2691A/MS2692A-313 Removable HDD

The MS269xA-313 Removable HDD is useful when a user takes the instrument to an outside company for calibration but wants to protect the security of data in the instrument, such as measurement results, data and main frame settings. In this case, the user removes the regular MS269xA hard disk and replaces it with this product.

Future-proof Platform (Software^{*})

Adding measurement software options to the signal analyzer assures that the modulation analysis and other functions will support all common current and future communications systems.

Measurement Software

Communications Systems	Model	Name		
Mobile WiMAX	MX269010A	Mobile WiMAX Measurement Software		
W-CDMA/	MX269011A	W-CDMA/HSPA Downlink Measurement Software		
Evolution	MX269012A	W-CDMA/HSPA Uplink Measurement Software		
W-CDMA/HSPA	MX269030A	W-CDMA BS Measurement Software		
GSM/EDGE	MX269013A	GSM/EDGE Measurement Software		
EDGE Evolution	MX269013A-001	EDGE Evolution Measurement Software		
ETC/DSRC	MX269014A	ETC/DSRC Measurement Software		
TD-SCDMA	MX269015A	TD-SCDMA Measurement Software		
Multi-TDMA systems	MX269017A	Vector Modulation Analysis Software		
	MX269020A	LTE Downlink Measurement Software		
3GPP LTE (FDD)	MX269020A-001	LTE-Advanced FDD Downlink Measurement Software		
	MX269021A	LTE Uplink Measurement Software		
	MX269022A	LTE TDD Downlink Measurement Software		
3GPP LTE (TDD)	MX269022A-001	LTE-Advanced TDD Downlink Measurement Software		
	MX269023A	LTE TDD Uplink Measurement Software		
CDMA2000	MX269024A	CDMA2000 Forward Link Measurement Software		
	MX269024A-001	All Measure Function		
1xEV-DO	MX269026A	EV-DO Forward Link Measurement Software		
	MX269026A-001	All Measure Function		
WLAN	MX269028A	WLAN (802.11) Measurement Software (Supports IEEE 802.11n/11a/11b/ 11g/11j/11p)		
	MX269028A-002*	802.11ac (160 MHz) Measurement Software (for MS269xA)		

*: Only for MS269xA.

Combining with the MS269xA-078 Analysis Bandwidth Extension to 125 MHz supports modulation analysis up to 160-MHz bandwidth signals of the IEEE 802.11ac.

*: See each software catalog for more details.

Measurement Software for Smart Meter

This software is for PC. This software supports automatic measurement of the PHY layer and protocol analysis of the PHY/ MAC layer of smart utility network wireless communications (Wi-SUN).

- MX705010A Wi-SUN PHY Measurement Software*1
- MX705110A Wi-SUN Protocol Monitor*2

The MX705010A*1 supports automatic measurement of Wi-SUN Alliance PHY Conformance test cases. The MS269xA is controlled by remote commands from this software

*1: Cannot be installed in MS269xA. Requires the latest firmware of MS269xA. Requires MX269017A, MS269xA-020 and MX269902A.

MX705110A^{*2} is possible to check the details of a Wi-SUN protocol. The wireless signals^{*3} between communicating wireless equipments are captured as I/Q data using the MS269xA digitize function and data analysis is performed by this software. Data analysis displays the PHY/MAC frame format, Tx timing, etc.

*2: Cannot be installed in MS269xA. Requires the latest firmware of MS269xA.

*3: IEEE 802.15.4g/e (GFSK)

Adding a license for the IQproducer waveform generation software to the vector signal generator option supports easy generation of test patterns for all common communications systems worldwide.

IQproducer License for MS269xA-020 VSG

Waveforms generated by IQproducer can be downloaded to the MS269xA main frame in which the MS269xA-020 Vector Signal Generator is installed, but the following licenses (option) are required to output the signal.

TDMA IQproducer

LTE IQproducer

HSDPA/HSUPA IQproducer

Multi-Carrier IQproducer

Mobile WiMAX IQproducer

LTE-Advanced FDD Option

LTE TDD IQproducer

- MX269901A
- MX269902A
- MX269904A
- MX269905A
- MX269908A
- MX269908A-001*1
- MX269910A
- MX269910A-001*2
- LTE-Advanced TDD Option • MX269911A
- WLAN IQproducer • MX269911A-001*3
 - 802.11ac (80 MHz) Option **TD-SCDMA** IQproducer
- MX269912A
- *1: Requires MX269908A.
- *2: Requires MX269910A.
- *3: Requires MX269911A.

Waveform Patterns for MS269xA-020 VSG

Various waveforms with preset parameters matching each communication method are provided. The MS269xA-020 Vector Signal Generator option outputs RF signals. Pre-installed reference waveforms are saved on the MS269xA hard disk for free use.

Pre-installed Patterns

- W-CDMA
- HSDPA (Test Model5)
- CDMA2000 1xEV-DO
- CDMA2000
- GSM/EDGE
- Digital Broadcasting (ISDB-T/CS/BS/CATV)
- WLAN (IEEE 802.11a/b/g)
- Bluetooth
- Option Patterns
 - MX269970A 1xEV-DO Reverse Receiver Test Waveform Pattern

Specifications

The specification is the value after a 30-minute warm-up at a constant ambient temperature. Typical values are only for reference and are not guaranteed specifications.

Vector Signal Analysis Function/Spectrum Analyzer Function Common

Frequency

Frequency Range	50 Hz to 6.0 GHz (MS2690A) 50 Hz to 13.5 GHz (MS2691A) 50 Hz to 26.5 GHz (MS2692A)						
	Frequency	Band	Mixer harmonic order (N)				
	50 Hz ≤ Frequency ≤ 6.0 GHz	0	1				
Francisco Dan da	3.0 GHz ≤ Frequency ≤ 6.0 GHz	1 – L	1	(with MS2691A-003/MS2692A-003, MS2691A/MS2692A)			
Frequency Bands	5.9 GHz ≤ Frequency ≤ 8.0 GHz	1–	1	(MS2691A/MS2692A)			
	7.9 GHz ≤ Frequency ≤ 13.5 GHz	1+	1	(MS2691A/MS2692A)			
	13.4 GHz ≤ Frequency ≤ 20.0 GHz	2–	2	(MS2692A)			
	19.9 GHz ≤ Frequency ≤ 26.5 GHz	2+	2	(MS2692A)			
Preselector Range	5.9 GHz to 13.5 GHz (Frequency band mode: Normal) (MS2691A) 5.9 GHz to 26.5 GHz (Frequency band mode: Normal) (MS2692A) 3.0 GHz to 13.5 GHz (Frequency band mode: Spurious) (MS2691A) 3.0 GHz to 26.5 GHz (Frequency band mode: Spurious) (MS2692A)						
Frequency Setting Range	0 Hz to 6.0 GHz (MS2690A) 0 Hz to 13.5 GHz (MS2691A) 0 Hz to 26.5 GHz (MS2692A) Setting resolution: 1 Hz						
Internal Reference Oscillator	Start-up characteristics (23°C, referenced to frequency at 24 h after power-on): ±5 x 10 ⁻⁷ (2 minutes after power-on), ±5 x 10 ⁻⁸ (5 minutes after power-on) Aging rate: ±1 x 10 ⁻⁷ /year, ±1 x 10 ⁻⁸ /day Temperature characteristics: ±2 x 10 ⁻⁸ (5' to 45°C) with MS269xA-001 Rubidium Reference Oscillator Start-up characteristics (23°C, referenced to frequency at 24 h after power-on): ±1 x 10 ⁻⁹ (7 minutes after power-on) Aging rate: ±1 x 10 ⁻¹⁰ /month Tomporature characteristics: ±1 x 10 ⁻⁹ (5' to 45°C)						
SSB Phase Noise	18° to 28°C, 2 GHz Frequency Offset Max. 100 kHz -116 dBc/Hz 1 MHz -137 dBc/Hz						

Amplitude

Measurement Range	without MS269xA-008, or Preamp: Off DANL to +30 dBm with MS269xA-008, Preamp: On DANL to +10 dBm
Max. Input Level	without MS269xA-008, or Preamp: Off CW Average power: +30 dBm (Input attenuator: ≥10 dB) DC Voltage: 0 Vdc
	with MS269xA-008, Preamp: On CW Average power: +10 dBm (Input attenuator: 0 dB) DC Voltage: 0 Vdc
Input Attenuator	0 to 60 dB, 2 dB steps
Input Attenuator Switching Error	Referenced to 10 dB input attenuator without MS269xA-008, or Preamp: Off Frequency band mode: Normal $\pm 0.2 \text{ dB}$ ($\leq 6.0 \text{ GHz}$, 10 to 60 dB) $\pm 0.75 \text{ dB}$ ($\geq 6.0 \text{ GHz}$, 10 to 60 dB) Frequency band mode: Spurious $\pm 0.2 \text{ dB}$ ($< 3.0 \text{ GHz}$, 10 to 60 dB) $\pm 0.75 \text{ dB}$ ($\geq 3.0 \text{ GHz}$, 10 to 60 dB)
	with MS269xA-008, Preamp: On Frequency band mode: Normal ±0.65 dB (≤6.0 GHz, 10 to 60 dB)

Vector Signal Analysis Function/Spectrum Analyzer Function Common (Continuation) Reference Level

Setting Range	ge Log scale: –120 to +50 dBm, or Equivalent level Linear scale: 22.4 μV to 70.7 V, or Equivalent level Setting resolution: 0.01 dB, or Equivalent level		
Units	Log scale: dBm, dBµV, dBµV, dBµV (emf), dBµV/m, V, W Linear scale: V		
Linearity Error	Excluding the noise floor effect without MS269xA-008, or Preamp: Off $\pm 0.07 \text{ dB}$ (Mixer input level: \leq -20 dBm) $\pm 0.10 \text{ dB}$ (Mixer input level: \leq -10 dBm) Frequency band mode: Normal, Mixer input level: ≤ 0 dBm $\pm 0.15 \text{ dB}$ ($\leq 6.0 \text{ GHz}$) $\pm 0.50 \text{ dB}$ ($\geq 6.0 \text{ GHz}$) (MS2691A) $\pm 0.60 \text{ dB}$ ($\geq 6.0 \text{ GHz}$) (MS2692A) Frequency band mode: Spurious, Mixer input level: $\leq 0 \text{ dBm}$ $\pm 0.15 \text{ dB}$ ($\leq 3.0 \text{ GHz}$) $\pm 0.50 \text{ dB}$ ($\geq 3.0 \text{ GHz}$) (MS2691A) $\pm 0.60 \text{ dB}$ ($\geq 3.0 \text{ GHz}$) (MS2692A) with MS269xA-008, Preamp: On $\pm 0.07 \text{ dB}$ (Preamp input level: \leq -40 dBm) $\pm 0.10 \text{ dB}$ (Preamp input level: \leq -30 dBm)		
RF Frequency Characteristics	Frequency band mode: Normal ±0.50 dB (Preamp input level: ≤–20 dBm, ≤6.0 GHz) 18* to 28*C, after CAL, Input attenuator: 10 dB without MS269xA-008, or Preamp: Off ±0.35 dB (9 kHz ≤ Frequency ≤ 6.0 GHz, Frequency band mode: Normal) (9 kHz ≤ Frequency < 3.0 GHz, Frequency band mode: Spurious)		
1 dB Gain Compression	without MS269xA-008, or Preamp: Off, Mixer input level ≥+3 dBm (100 MHz ≤ Frequency < 400 MHz)		

Spurious Response

	without MS260vA 009, or Proome: Off Mixer input lovel: 20 dPm				
	Harmonic (dBc)	SHI (dBm)			
	≤–60	≥+30	(10 Hz ≤ Frequency ≤ 400 MHz)		
	≤–75	≥+45	$(400 \text{ MHz} < \text{Frequency} \le 3.0 \text{ GHz})$		
	without MS2692A-067, Mixer input level: -10 dBm				
	Harmonic (dBc)	SHI (dBm)			
	≤–90	≥+80	(>3.0 GHz, Frequency band mode: Normal)		
2nd Harmonic Distortion	≤–90	≥+80	(≥1.5 GHz, Frequency band mode: Spurious)		
	with MS2692A-067, Microwave Preselector Bypass: Off, Mixer input level: -10 dBm				
	Harmonic (dBc)	SHI (dBm)			
	≤–70	≥+60	(3 GHz < Frequency ≤ 13.25 GHz)		
	with MS269xA-008, Preamp: On, Preamp input level: -45 dBm				
	Harmonic (dBc)	SHI (dBm)			
	≤–50	≥+5	(10 Hz ≤ Frequency ≤ 400 MHz)		
	≤–55	≥+10	(400 MHz < Frequency \leq 3.0 GHz)		
	Frequency: ≥1 MHz,	Input attenuator: 0	dB, 50Ω terminated		
Residual Response	Signal Analyzer: with	n MS269xA-077/078	8, Except bandwidth setting: >31.25 MHz		
·	≤–100 dBm				

ОРУДОВАНИЕ

ГРУППА КОМПАНИЙ

Vector Signal Analysis Function/Spectrum Analyzer Function Common (Continuation) Connector

	Front page N-1 500 (nominal)
RF Input	18° to 28°C Input attenuator: >10 dB
	VSWP- <12 (monitorial 40 MHz $<$ Erequency <30 GHz)
	≤ 15 (nominal 3.0 GHz < Frequency < 6.0 GHz)
	≤ 2.0 (nominal 6.0 GHz \leq Frequency ≤ 26.5 GHz)
	Por page INC 500 Chi antequency 20:0012)
	Real parter, DNC-0, JOS2 (IIOIIIIIa) Erequiparty 725 MHz (Circuit Academic without MS260vA 077/078, or Bondwidth: <24.25 MHz)
	000 MHz (Gignal Analyzer, with 0209X+077/079, Dandwidth: 301.25 MHz)
IF Output	900 WHZ (Sopratum Analyzet, With WSZ09XA-0/1/0/6, Balidwidth, S51.25 WHZ)
	or4.300 km/z (Specium Analyzer)
	Gaint 0 db (informinal) (Referenced to RF input level, RF frequency. T Grz, input altendator. 0 db)
	Rear panel, BNC-J, 50/2 (nominal)
External Reference Input	requency: 10 MHz,13 MHz
	Operation range: ±1 ppm
	Input level: −15 dBm ≤ Level ≤ +20 dBm, 50Ω (AC coupling)
	Rear panel, BNC-J, 50Ω (nominal)
Reference Signal Output	Frequency: 10 MHz
	Output level: ≥0 dBm (AC coupling)
Sween Status Output	Rear panel, BNC-J
	Output level: TTL Level (High level at sweeping or waveform capture)
Triggor Input	Rear panel, BNC-J
nigger niput	Input level: TTL Level
	This is available when the Option 017/117 is installed.
Naisa Causa Daisa	Supply(+28 V) of the Noise Source Drive.
Noise Source Drive	Rear Panel, BNC-J
	Output Voltage: 28 ±0.5 V, Pulsed
	Control from external controller (Excluding power-on)
	Ethernet 10/100/BASE-T, Rear panel, RJ-45
External Reference	GPIB: IEEE 488.2, Rear panel, IEEE 488 bus connector
	Interface functions: SH1, AH1, T6, L4, SR1, RL1, PP0, DC1, DT0, C0, E2
	USB (B): USB2.0, Rear panel, USB-B connector
	USB2 0 Supporting waveform hard copy to external device, and saving main frame settings
USB	USB-A connector (Front panel: 2 ports, Rear panel: 2 ports)
Monitor Output	Rear panel VGA compatible mini D-Sub 15 pin
	When using MS269x4.020 triager input/output
Aux	Rear name (88 noise) (DX10BL-685 envirolent)
Diaplay	VCA aplant CD (424 x 35 readition) 9.4 inch (212 mm)
Dispidy	AGA-COIOL LOD (1024 × 700 TESOIUIIOT), 6.4 INCH (213 INTH)

General Specifications

Dimensions and Mass	340 (W) × 200 (H) × 350 (D) mm (Excluding projections), ≤13.5 kg (Excluding options)	
Power Supply	100 V(ac) to 120 V(ac), 200 V(ac) to 240 V(ac) (-15/+10%, 250 V max.), 50 Hz/60 Hz (±5%)	
	≤260 VA (Excluding options), ≤440 VA (Including all options, max.)	
Temperature Range	Operating: +5° to +45°C, Storage: -20° to +60°C	
EMC	EN61326-1, EN61000-3-2	
LVD	EN61010-1	

Spectrum Analyzer Function

Frequency

Span	Range: 0 Hz, 300 Hz to 6.0 GHz (MS2690A)
	0 Hz, 300 Hz to 13.5 GHz (MS2691A)
	0 Hz, 300 Hz to 26.5 GHz (MS2692A)
	Resolution: 2 Hz
	Accuracy: ±0.2% (Number of Trace points: 10001)
	± [Display frequency × Reference oscillator accuracy + Span frequency × Span accuracy + RBW × 0.05 + 2 × N
Display Frequency Accuracy	+ Span frequency/(Number of trace points – 1)] Hz
	N: Mixer harmonic order
Decelution Dondwidth	Setting range: 30 Hz to 3 MHz (1-3 sequence), 50 kHz, 5, 10, 20, 31.25 MHz
(RBW)	*31.25 MHz: Can be set when Span: 0 Hz only
	Selectivity (–60 dB/–3 dB): 4.5:1 (Nominal, 30 Hz to 10 MHz)
Video Dondwidth (V(D)M)	Setting range: 1 Hz to 10 MHz (1-3 sequence), 5 kHz, Off
Video Bandwidth (VBW)	VBW mode: Video Average, Power Average

Amplitude

	18° to 28°C, Detector: Sample, VBW: 1	Hz (Video Average), I	Input attenuator: 0 dB
	without MS269xA-008, 6.0 GHz ≤ Freq	uency ≤ 26.5 GHz: wit	hout MS2692A-067
	Frequency	Max.	Frequency band mode
	100 kHz	–135.0 [dBm/Hz]	
	1 MHz	-145.0 [dBm/Hz]	
	30 MHz ≤ Frequency < 2.4 GHz	-155.0 [dBm/Hz]	
	2.4 GHz ≤ Frequency < 3.0 GHz	-153.0 [dBm/Hz]	
	3.0 GHz ≤ Frequency < 4.0 GHz	-153.0 [dBm/Hz]	Normal
	4.0 GHz ≤ Frequency < 6.0 GHz	-152.0 [dBm/Hz]	Normal
	6.0 GHz ≤ Frequency < 10.0 GHz	-151.0 [dBm/Hz]	Normal
	10.0 GHz ≤ Frequency ≤ 13.5 GHz	-150.0 [dBm/Hz]	Normal
	13.5 GHz < Frequency ≤ 20.0 GHz	-147.0 [dBm/Hz]	Normal
	20.0 GHz < Frequency ≤ 26.5 GHz	-143.0 [dBm/Hz]	Normal
	with MS269xA-008, Preamp: On		
	Frequency	Max.	Frequency band mode
Displayed Average Noise	100 kHz	-150.0 [dBm/Hz]	
Level (DANL)	1 MHz	-159.0 [dBm/Hz]	
	30 MHz ≤ Frequency < 2.4 GHz	-166.0 [dBm/Hz]	
	2.4 GHz ≤ Frequency < 3.0 GHz	-165.0 [dBm/Hz]	
	3.0 GHz ≤ Frequency < 4.0 GHz	-164.0 [dBm/Hz]	Normal
	4.0 GHz ≤ Frequency < 5.0 GHz	-161.0 [dBm/Hz]	Normal
	5.0 GHz \leq Frequency \leq 6.0 GHz	-159.0 [dBm/Hz]	Normal
	with MS269xA-008, Preamp: Off		
	Frequency	Max.	Frequency band mode
	100 kHz	-135.0 [dBm/Hz]	
	1 MHz	-145.0 [dBm/Hz]	
	30 MHz ≤ Frequency < 2.4 GHz	-153.0 [dBm/Hz]	
	2.4 GHz ≤ Frequency < 3.0 GHz	-152.0 [dBm/Hz]	
	3.0 GHz ≤ Frequency < 4.0 GHz	-151.0 [dBm/Hz]	Normal
	4.0 GHz ≤ Frequency < 5.0 GHz	-150.0 [dBm/Hz]	Normal
	5.0 GHz ≤ Frequency < 6.0 GHz	-149.0 [dBm/Hz]	Normal
	18° to 28°C, after CAL, Input attenuator Detection: Positive, CW, Excluding the	: ≥10 dB, Auto Sweep noise floor effect	Time Select: Normal, RB
	without MS269xA-008 Preamp: Off		
T () () ()	Mixer input level: <0 dBm		
I otal Level Accuracy*	$\pm 0.5 \text{ dB}$ (50 Hz \leq Frequency $\leq 6.0 \text{ GF}$	Iz. Frequency band m	ode: Normal)
*: The Total level accuracy	(50 Hz ≤ Frequency < 3.0 GF	Iz, Frequency band m	ode: Spurious)
is found from root sum of	after Preselector tuning		
squares (RSS) of RF	±1.8 dB (6.0 GHz < Frequency ≤ 13.5	GHz, Frequency ban	d mode: Normal)
error and input attenuator	$(3.0 \text{ GHz} \le \text{Frequency} \le 13.5)$	GHz, Frequency ban	d mode: Spurious)
switching error	$\pm 3.0 \text{ dB}$ (13.5 GHz < Frequency $\leq 26.$.5 GHz)	
errer ing erreri	with MS269xA-008, Preamp: On		
	Preamp input level: ≤–20 dBm	ou = · ·	
	$\pm 1.0 \text{ dB}$ (100 kHz \leq Frequency $\leq 6.0 \text{ G}$	Hz, Frequency band	mode: Normal)
	$(100 \text{ kHz} \le \text{Frequency} < 3.0)$	SILZ, Frequency band	mode: Spurious)

Spectrum Analyzer Function (Continuation) Spurious Response

	18° to 28°C, ≥300 kHz separation
	without MS269xA-008, or Preamp: Off
	with MS2692A-067, Microwave Preselector Bypass: Off
	Mixer input level: -15 dBm (per waveform)
	≤–60 dBc (TOI: +15 dBm) (30 MHz ≤ Frequency < 400 MHz)
	≤–66 dBc (TOI: +18 dBm) (400 MHz ≤ Frequency < 700 MHz)
	≤–74 dBc (TOI: +22 dBm) (700 MHz ≤ Frequency < 4.0 GHz, Frequency band mode: Normal)
	(700 MHz \leq Frequency $<$ 3.0 GHz, Frequency band mode: Spurious)
2-tone 3rd-order	≤–66 dBc (TOI: +18 dBm) (4.0 GHz ≤ Frequency ≤ 6.0 GHz, Frequency band mode: Normal)
Intermodulation Distortion	≤–45 dBc (TOI: +7.5 dBm) (6.0 GHz < Frequency ≤ 26.5 GHz, Frequency band mode: Normal)
	(3.0 GHz \leq Frequency \leq 26.5 GHz, Frequency band mode: Spurious)
	with MS269xA-008, Preamp: On
	Preamp input level: –45 dBm (per waveform)
	≤–73 dBc (TOI: –8.5 dBm) (30 MHz ≤ Frequency < 400 MHz)
	≤–78 dBc (TOI: –6 dBm) (400 MHz ≤ Frequency < 700 MHz)
	≤–81 dBc (TOI: –4.5 dBm) (700 MHz ≤ Frequency < 4.0 GHz, Frequency band mode: Normal)
	(700 MHz ≤ Frequency < 3.0 GHz, Frequency band mode: Spurious)
	≤–78 dBc (TOI: –6 dBm) (4.0 GHz ≤ Frequency ≤ 6.0 GHz, Frequency band mode: Normal)
	without MS2692A-067
Image Response	\leq -70 dBc (Frequency \leq 13.5 GHz)
	≤-65 dBc (13.5 GHz < Frequency ≤ 26.5 GHz)

Sweep

Sweep Mode	Single, Continuous
Sweep Time	Setting range: 2 ms to 1000 s (Span: ≥300 Hz), 1 µs to 1000 s (Span: 0 Hz)

Waveform Display

Detector	Pos&Neg, Positive Peak, Sample, Negative Peak, RMS		
	1001, 2001, 5001, 10001 (Span: >500 MHz)		
	101, 201, 251, 401, 501, 1001, 2001, 5001, 10001 (100 MHz < Span ≤ 500 MHz)		
Number of Trees Deinte	(300 Hz ≤ Span ≤ 100 MHz, Sweep time: >10 s)		
Number of Trace Points	11, 21, 41, 51, 101, 201, 251, 401, 501, 1001, 2001, 5001, 10001 (300 Hz ≤ Span ≤ 100 MHz, Sweep time: ≤10 s)		
	(Span: 0 Hz, Sweep time: ≤10 s)		
	101, 201, 251, 401, 501, 1001, 2001, 5001, 10001 (Span: 0 Hz, Sweep time: >10 s)		
Saala	Log display: 10 div/12 div, 0.1 to 20 dB/div (1-2-5 sequence)		
Scale	Lin display: 10 div, 1 to 10%/div (1-2-5 sequence)		
Trigger Function	Trigger mode: Free Run (Trig Off), Video, Wide IF, External (TTL)		
	SG Marker (with MS269xA-020), BBIF (with MS269xA-040)		
Osta Eventina	Gate mode: Off, Wide IF, External		
Gate Function	SG Marker (with MS269xA-020), BBIF (with MS269xA-040)		

Measurement Functions

Adjacent Channel		Reference: Span Total, Carrier Total, Both side of Carrier, Carrier Select	
Leakage Power (ACP)		Adjacent channel specification: 3 channels × 2 (Normal Mode), 8 channels × 2 (Advanced Mode)	
Burst Average Power		In time domain, displays average power in specified time	
Channel Power		Absolute value measurement: dBm, dBm/Hz	
Occupied Bandwidth (OBW)		N% of Power, X-dB Down	
Spectrum Emission Mask		Pass/Fail evaluation at Peak/Margin measurement	
Spurious Emission		Pass/Fail evaluation at Worst/Peaks measurement	
		Span: ≤1 MHz, RBW: 1 kHz, S/N: ≥50 dB, Gate time: ≥100 ms,	
F	Accuracy	± (Marker frequency × Frequency reference accuracy + (0.01 × N/Gate Time[s]) Hz)	
Frequency Counter		N: Mixer harmonic order	
	Gate Time	100 up to 1 p	
	Range	100 µ5 to 1 5	
2-tone 3rd-order		Massures IM3 and TOI from two-tone signal	
Intermodulation Distortion			

Vector Signal Analysis Function

Common

Trace Mode	Spectrum, Power vs. Time, Frequency vs. Time, Phase vs. Time, CCDF, Spectrogram, No Trace		
	without MS269xA-077/078 Specified analysis bandwidth from center frequency 1 kHz to 25 MHz (1-2.5-5 sequence), 31.25 MHz		
Bandwidth	with MS269xA-077 Adds the 50 MHz, 62.5 MHz bandwidths to the standard analysis bandwidths.		
	with MS269xA-077/078 Adds the 50, 62.5, 100, and 125 MHz bandwidths to the standard analysis bandwidths.		
	Auto-setting depending on RBW		
	without MS269xA-077/078, or Bandwidth: ≤31.25 MHz 2 kHz to 50 MHz (1-2-5 sequence)		
Sampling Rate	with MS269xA-077, Bandwidth: >31.25 MHz 100 MHz		
	with MS269xA-077/078, Bandwidth: >31.25 MHz 100 MHz, 200 MHz		
	Set length of capture time		
	without MS269xA-077/078, or Bandwidth: ≤31.25 MHz Min. capture time length: 2 µs to 50 ms (determined depending on analysis bandwidth) Max. capture time length: 2 to 2000 s (determined depending on analysis bandwidth) Setting mode: Auto, Manual		
Capture Time	with MS269xA-077, Bandwidth: >31.25 MHz Min. capture time length: 1 μs (determined depending on analysis bandwidth) Max. capture time length: 500 ms		
	with MS269xA-077/078, Bandwidth: >31.25 MHz Min. capture time length: 500 ns to 1 μs (determined depending on analysis bandwidth) Max. capture time length: 500 ms		
Trigger	Trigger mode: Free Run (Trig Off), Video, Wide IF Video, External (TTL) SG Marker (with MS269xA-020), BBIF (with MS269xA-040)		
ADC Resolution	16 bits		

Spectrum Display Function

Function Outline	Displays any time length in captured waveform data and spectrum in frequency range		
	Analysis start time: Set analysis start time point from waveform data header		
Analysis Time Range	Analysis time length: Set analysis time length		
	Setting mode: Auto, Manual		
Frequency	Set center frequency and Span in frequency range of waveform data		
	without MS269xA-077/078, or Bandwidth: ≤31.25 MHz		
	0 Hz to 6.0 GHz (MS2690A), 0 Hz to 13.5 GHz (MS2691A), 0 Hz to 26.5 GHz (MS2692A)		
F O # D	with MS269xA-077, or with MS269xA-077/078, without MS2692A-067, Bandwidth: >31.25 MHz		
Frequency Setting Range	100 MHz to 6.0 GHz		
	with MS269xA-077. or with MS269xA-077/078. with MS2692A-067. Bandwidth: >31.25 MHz		
	100 MHz to 26.5 GHz		
	without MS269xA-077/078, or Bandwidth: ≤31.25 MHz		
	Setting range: 1 Hz to 1 MHz (1-3 sequence)		
	Selectivity (-60 dB/-3 dB): 4.5:1 (nominal)		
	with MS269xA-077, Bandwidth: >31.25 MHz		
Resolution Bandwidth	Setting range: 3 kHz to 3 MHz (1-3 sequence)		
(RBW)	Selectivity (–60 dB/–3 dB): 4.5:1 (nominal)		
	with MS269xA-077/078. Bandwidth: >31.25 MHz		
	Setting range: 3 kHz to 10 MHz (1-3 sequence)		
	Selectivity (-60 dB/-3 dB): 4.5:1 (nominal)		

Vector Signal Analysis Function (Continuation) Spectrum Display Function (Continuation)

Spectrum Display Fund							
	18° to 28°C, after CAL, Input attenuator: ≥10 dB, Center frequency, CW, RBW: Auto, Time Detection: Average, Marker Result: Integration or Peak (Accuracy), Excluding the noise floor effect						
	Mixer input level: ≤0 dBm						
	without MS269xA-077/078, or Bandwidth: ≤31.25 MHz						
	without MS269xA-008, or Preamp: Off	– F asarian and as	a da . Na ma al)				
	±0.5 dB (50 Hz ≤ Frequency ≤ 6.0 GHz, Frequency band mode: Normal) (50 Hz ≤ Frequency < 3.0 GHz, Frequency band mode: Spurious)						
	after Preselector tuning ±1.8 dB (6.0 GHz < Frequency ≤ 13.5	GHz. Frequency ban	d mode: Normal)				
Total Level Accuracy*	(3.0 GHz \leq Frequency \leq 13.5 GHz, Frequency band mode: Spurious) ±3.0 dB (13.5 GHz \leq Frequency \leq 26.5 GHz)						
*: The Total level accuracy	with MS269xA-077, or with MS269xA-077/078, Bandwidth: >31.25 MHz						
is found from root sum of	without MS269xA-008, or Preamp: Off						
characteristics linearity	±0.5 dB (100 MHz ≤ Frequency ≤ 6.0 GHz, Frequency band mode: Normal)						
error, and input attenuator	with MS269xA-077, or with MS269xA-0	77/078					
switching error.	with MS2692A-067, Microwave Presele	ctor Bypass: On, Ban	dwidth: >31.25 MHz				
	$\pm 3.0 \text{ dB}$ (13.5 GHz \leq Frequency \leq 13.5 $\pm 3.0 \text{ dB}$ (13.5 GHz \leq Frequency \leq 26.	5 GHz)	u mode. Normar)				
	Preamp input level: ≤–20 dBm						
	without MS269xA-077/078, or Bandwid	th: ≤31.25 MHz					
	with MS269xA-008, Preamp: On		modo: Normal)				
	± 1.0 dB (100 kHz \leq Frequency ≤ 0.0 (100 kHz \leq Frequency < 3.0 (GHz, Frequency band	mode: Spurious)				
	with MS269xA-077 or with MS269xA-0	77/078 Bandwidth: >:	31 25 MHz				
	with MS269xA-008, Preamp: On	rivero, Banamath. 20					
	$\pm 1.0 \text{ dB}$ (100 MHz \leq Frequency ≤ 6.0	GHz, Frequency band	d mode: Normal)				
	18° to 28°C, Input attenuator: 0 dB						
	without MS269xA-008, 6.0 GHz ≤ Frequency ≤ 26.5 GHz: without MS2692A-067						
	Frequency	Max.	Frequency band mode				
	100 kHz	–132.5 [dBm/Hz]		-			
	1 MHz	-142.5 [dBm/Hz]		-			
	$30 \text{ MHz} \le \text{Frequency} < 2.4 \text{ GHz}$	-152.5 [dBm/Hz]		-			
	$2.4 \text{ GHz} \le \text{Frequency} < 3.0 \text{ GHz}$	-150.5 [dBm/Hz]	Normal	-			
	$3.0 \text{ GHz} \leq \text{Frequency} \leq 6.0 \text{ GHz}$	-130.5 [dBm/Hz]	Normal	-			
	$6.0 \text{ GHz} \leq \text{Frequency} < 0.0 \text{ GHz}$	-148.5 [dBm/Hz]	Normal				
	$10.0 \text{ GHz} \leq \text{Frequency} \leq 13.5 \text{ GHz}$	-147.5 [dBm/Hz]	Normal	-			
	13.5 GHz < Frequency ≤ 20.0 GHz	–144.5 [dBm/Hz]	Normal	-			
	20.0 GHz < Frequency ≤ 26.5 GHz	–140.5 [dBm/Hz]	Normal				
	with MS269xA-008, Preamp: On						
Displayed Average Maine	Frequency	Max.	Frequency band mode				
Level (DANI.)	100 kHz	–147.5 [dBm/Hz]		_			
	1 MHz	-156.5 [dBm/Hz]		-			
	30 MHz ≤ Frequency < 2.4 GHz	-163.5 [dBm/Hz]		-			
	$2.4 \text{ GHz} \le \text{Frequency} < 3.0 \text{ GHz}$	-162.5 [dBm/Hz]	Normal	-			
	$4.0 \text{ GHz} \leq \text{Frequency} < 5.0 \text{ GHz}$	-161.5 [uBIII/H2] -158 5 [dBm/Hz]	Normal	-			
	$5.0 \text{ GHz} \leq \text{Frequency} \leq 6.0 \text{ GHz}$	-156.5 [dBm/Hz]	Normal				
	$\frac{1}{10000000000000000000000000000000000$						
	Frequency	Max	Frequency band mode]			
	100 kHz	-132.5 [dBm/Hz]					
	1 MHz	-142.5 [dBm/Hz]		-			
	30 MHz ≤ Frequency < 2.4 GHz	–150.5 [dBm/Hz]					
	2.4 GHz ≤ Frequency < 3.0 GHz	-149.5 [dBm/Hz]					
	3.0 GHz ≤ Frequency < 4.0 GHz	–148.5 [dBm/Hz]	Normal				
	$4.0 \text{ GHz} \le \text{Frequency} < 5.0 \text{ GHz}$	-147.5 [dBm/Hz]	Normal	-			
	5.0 GHz \leq Frequency < 6.0 GHz	–146.5 [dBm/Hz]	Normal]			
Adjacent Channel Leakage Power Measurement (ACP)	Reference: Span Total, Carrier Total, B Adjacent channel specification: 3 channel	oth Sides of Carriers, nels × 2	Carrier Select				
Channel Power	Absolute value measurement: dBm, dBm/Hz						
Occupied Bandwidth (OBW)	N% of Power, × dB Down						

Vector Signal Analysis Function (Continuation)

Power vs. Time Display Function

Function Outline	Displays variation in power of captured waveform with time		
	Analysis start time: Sets analysis start time point from waveform data header		
Analysis Time Range	Analysis time length: Sets analysis time length		
	Setting mode: Auto, Manual		
	Filter type: Rect, Gaussian, Nyquist, Root Nyquist, Off, (Default: Off)		
Resolution Bandwidth	Roll-off ratio: 0.01 to 1 (Set for Nyquist, Root Nyquist)		
	Filter frequency offset: Set center frequency of filter in wavelength data frequency band		
AM Depth	Measures with AM depth or marker function		
(Peak to Peak Measurement)	+Peak, –Peak, (P-P)/2, Average		
Burst Average Power	Measures average power of burst signal		
Resolution Bandwidth AM Depth (Peak to Peak Measurement) Burst Average Power	Setting mode. Auto, Manual Filter type: Rect, Gaussian, Nyquist, Root Nyquist, Off, (Default: Off) Roll-off ratio: 0.01 to 1 (Set for Nyquist, Root Nyquist) Filter frequency offset: Set center frequency of filter in wavelength data frequency band Measures with AM depth or marker function +Peak, -Peak, (P-P)/2, Average Measures average power of burst signal		

Frequency vs. Time Display Function

Function Outline	Displays variation in frequency of input signal with time from captured waveform data		
	Analysis start time: Sets analysis start time point from waveform data header		
Analysis Time Range	Analysis time length: Sets analysis time length		
	Setting mode: Auto, Manual		
Operation Level Range	-17 to +30 dBm (Input attenuator: ≥10 dB)		
Frequency (Vertical axis)	Sets center frequency and Span in waveform data frequency range		
	Display frequency range: 1/25, 1/10, 1/5, 1/2 of RBW		
	Input frequency range: 10 MHz to 6 GHz		
	Input level: –17 to +30 dBm (Span: ≤31.25 MHz, Scale: Span/25)		
Display Frequency Accuracy	CW input: ± (Reference oscillator accuracy × Center frequency + Display frequency range × 0.01) Hz		
FM Deviation	Measures with FM deviation or marker function		
(Peak to Peak Measurement)	+Peak, –Peak, (P-P)/2, Average		

Phase vs. Time Display Function

Function Outline	Displays phase time fluctuation of input signal from captured waveform data		
	Analysis start time: Sets analysis start time point from waveform data header		
Analysis Time Range	Analysis time length: Sets analysis time length		
	Setting mode: Auto, Manual		
	Display mode: Wrap, Unwrap		
Phase (Vertical axis)	Display phase range: 0.01 deg./div to 200 Gdeg./div		
	Offset: -100 deg. to +100 Mdeg.		

CCDF/APD Display Function

Function Outline	Displays CCDF and APD of waveform data captures for fixed time		
	Analysis start time: Sets analysis start time point from waveform data header		
Analysis Time Range	Analysis time length: Sets analysis time length		
	Setting mode: Auto, Manual		
	Displays CCDF or APD as graph		
Display	Histogram resolution: 0.01 dB		
	Numeric display: Average Power, Max Power, Crest Factor		
Resolution Bandwidth	Filter type: Rectangle, Off, (Default: Off)		
(RBW)	Filter frequency offset: Sets filter center frequency in waveform data frequency band		

Spectrogram Display Function

Function Outline	Displays spectrogram for time period in captured waveform data
Analysis start time: Sets position of analysis start after waveform data header	
Analysis Time Range	Analysis time length: Sets analysis time length
	Setting mode: Auto, Manual
Frequency	Settable as center frequency and span frequency of waveform data
Resolution Bandwidth	Setting range: 1 Hz to 1 MHz (1-3 sequence)
(RBW)	Selection (-60/-3 dB): 4.5: 1 (nominal)

Digitize Function

Function Outline	Outputs captured waveform data to internal hard disk or external device		
Waveform Data	Format: I, Q (32 bit Float Binary format) Level: Sets 0 dBm input to $\sqrt{(l^2 + Q^2)} = 1$		
	Level accuracy. Same as Total level accuracy of Signal Analyzei		
External Output	Output to external PC via Ethernet		

Vector Signal Analysis Function (Continuation) Replay Function

Function Outline	Captured wave	Captured waveforms can be replayed again by using the VSA function to read saved digitize data			
	Format: I, Q (Bi	nary format)			
	Combination of Span, Sampling rate, and Minimum Capture Sample:				
	Span	Sampling Rate	Minimum (Capture Sample	
	1 kHz	2 kHz	74000	(37 s)	
	2.5 kHz	5 kHz	160000	(32 s)	
	5 kHz	10 kHz	310000	(31 s)	
	10 kHz	20 kHz	610000	(30.5 s)	
	25 kHz	50 kHz	730000	(14.6 s)	
	50 kHz	100 kHz	730000	(7.3 s)	
Measurable Waveform Data	100 kHz	200 kHz	730000	(3.65 s)	
	250 kHz	500 kHz	730000	(1.46 s)	
	500 kHz	1 MHz	730000	(730 ms)	
Condition	1 MHz	2 MHz	730000	(365 ms)	
	2.5 MHz	5 MHz	730000	(146 ms)	
	5 MHz	10 MHz	730000	(73 ms)	
	10 MHz	20 MHz	730000	(36.5 ms)	
	18.6 MHz	20 MHz	730000	(36.5 ms)	
	20 MHz	25 MHz	730000	(29.2 ms)	
	25 MHz	50 MHz	730000	(14.6 ms)	
	31.25 MHz	50 MHz	730000	(14.6 ms)	
	50 MHz	100 MHz	730000	(7.3 ms)	
	62.5 MHz	100 MHz	730000	(7.3 ms)	
	100 MHz	200 MHz	730000	(3.65 ms)	
	125 MHz	200 MHz	730000	(3.65 ms)	

Hardware Option

MS2690A/MS2691A/MS2692A-001 Rubidium Reference Oscillator

Function Outline Generates 10 MHz reference signal with higher frequency stability

MS2691A/MS2692A-003 Extension of Preselector Lower Limit to 3 GHz

Cannot be installed simultar	eously MS2692A-003 and MS2692A-067.
Function Outline	Extends lower limit of preselector to 3 GHz

MS2690A/MS2691A/MS2692A-008 6 GHz Preamplifier

Cannot be installed simultaneously MS2692A-008 and MS2692A-067.

Frequency

Range	100 kHz to 6 GHz
Amanditarda	
Amplitude	
Measurement Range	Displayed average noise level to +10 dBm
May Input Level	CW Average power: +10 dBm (Input attenuator: 0 dB)
Max. Input Level	DC Voltage: 0 Vdc
Cain	14 dB (Frequency ≤ 3.0 GHz), 13 dB (3.0 GHz < Frequency ≤ 4.0 GHz), 11 dB (4.0 GHz < Frequency ≤ 5.0 GHz),
Gain	10 dB (5.0 GHz < Frequency < 6.0 GHz)

	10 dB (5.0 GHz < Frequency ≤ 6.0 GHz)							
Noise Factor	7.0 dB (Frequency ≤ 3.0 GHz), 8.5 dB (3.0 GHz < Frequency ≤ 4.0 GHz), 9.5 dB (4.0 GHz < Frequency ≤ 6.0 GHz)							
	Spectrum analyzer function: 18° to 28°C, Input attenuator: 0 dB, Detector: sample, VBW: 1 Hz (Video average) Vector signal analysis function: 18° to 28°C, Input attenuator: 0 dB							
	Preamp: On							
	Frequency	Max. (Spectrum analyzer function)	Max. (Vector signal analysis function)	Frequency band mode				
	100 kHz	-150.0 [dBm/Hz]	–147.5 [dBm/Hz]					
	1 MHz	–159.0 [dBm/Hz]	–156.5 [dBm/Hz]					
	30 MHz ≤ Frequency < 2.4 GHz	-166.0 [dBm/Hz]	–163.5 [dBm/Hz]					
	2.4 GHz ≤ Frequency < 3.0 GHz	-165.0 [dBm/Hz]	-162.5 [dBm/Hz]					
Displayed Average Noise Level (DANL)	3.0 GHz ≤ Frequency < 4.0 GHz	-164.0 [dBm/Hz]	–161.5 [dBm/Hz]	Normal				
	4.0 GHz ≤ Frequency < 5.0 GHz	-161.0 [dBm/Hz]	–158.5 [dBm/Hz]	Normal				
	5.0 GHz ≤ Frequency ≤ 6.0 GHz	-159.0 [dBm/Hz]	-156.5 [dBm/Hz]	Normal				
	Preamp: Off							
	Frequency	Max. (Spectrum	Max. (Vector signal	Frequency band mode				
	- Trequency	analyzer function)	analysis function)	Trequency band mode				
	100 kHz	-135.0 [dBm/Hz]	–132.5 [dBm/Hz]					
	1 MHz	-145.0 [dBm/Hz]	-142.5 [dBm/Hz]					
	30 MHz ≤ Frequency < 2.4 GHz	–153.0 [dBm/Hz]	–150.5 [dBm/Hz]					
	2.4 GHz ≤ Frequency < 3.0 GHz	–152.0 [dBm/Hz]	-149.5 [dBm/Hz]					
	3.0 GHz ≤ Frequency < 4.0 GHz	-151.0 [dBm/Hz]	-148.5 [dBm/Hz]	Normal				
	4.0 GHz ≤ Frequency < 5.0 GHz	-150.0 [dBm/Hz]	-147.5 [dBm/Hz]	Normal				
	5.0 GHz ≤ Frequency < 6.0 GHz	-149.0 [dBm/Hz]	-146.5 [dBm/Hz]	Normal				
Input Attenuator	Frequency band mode: Normal							
Switching Error	±0.65 dB (≤6.0 GHz, 10 to 60 dB)							

Reference Level

RF Frequency	18° to 28°C, After CAL, Input attenuator: 10 dB ±0.65 dB (100 kHz ≤ Frequency ≤ 6.0 GHz, Frequency band mode: Normal)			
Characteristics	(100 kHz ≤ Frequency < 3.0 GHz, Frequency band mode: Spurious)			
	Excluding the noise floor effect			
	±0.07 dB (Preamp input level*: ≤–40 dBm)			
Linearity Error	±0.10 dB (Preamp input level*: ≤–30 dBm)			
	Frequency band mode: Normal			
	±0.5 dB (Preamp input level*: ≤–20 dBm, frequency: ≤6.0 GHz)			
	Preamp input level*			
1 dB Gain Compression	≥–20 dBm (100 MHz ≤ Frequency < 400 MHz)			
	≥–15 dBm (400 MHz ≤ Frequency ≤ 6.0 GHz, Frequency band mode: Normal)			
	(400 MHz \leq Frequency $<$ 3.0 GHz, Frequency band mode: Spurious)			

Hardware Option (Continuation)

2nd Harmonic Distortion	Preamp input level*: -45 dBm
	Harmonic SHI
	≤–50 dBc ≥+5 dBm (10 Hz ≤ Frequency ≤ 400 MHz)
	≤–55 dBc ≥+10 dBm (400 MHz < Frequency ≤ 3.0 GHz)
2-tone 3rd-order Intermodulation Distortion	18° to 28°C, Preamp input level*: -45 dBm (per waveform), ≥300 kHz separation
	≤–73 dBc (TOI: –8.5 dBm) (30 MHz ≤ Frequency < 400 MHz)
	≤–78 dBc (TOI: –6 dBm) (400 MHz ≤ Frequency < 700 MHz)
	≤–81 dBc (TOI: –4.5 dBm) (700 MHz ≤ Frequency < 4.0 GHz, Frequency band mode: Normal)
	(700 MHz \leq Frequency $<$ 3.0 GHz, Frequency band mode: Spurious)
	≤–78 dBc (TOI: –6 dBm) (4.0 GHz ≤ Frequency ≤ 6.0 GHz, Frequency band mode: Normal)

*: Preamp input level = RF input level - Input attenuator setting value

MS2690A/MS2691A/MS2692A-017 Noise Figure Measurement Function*

Frequency

-	
Frequency range	MS2690A: 30 MHz to 6 GHz
	MS2691A: 30 MHz to 6 GHz
	MS2692A: 30 MHz to 6 GHz
Frequency setting range	MS2690A: 10 MHz to 6 GHz
	MS2691A: 10 MHz to 13.5 GHz
	MS2692A: 10 MHz to 26.5 GHz

NF Measurement

Measurement range	Within the frequency range (Attenuator = 0 dB, Pre-Amp = On) - 20 to +40 dB
Instrument Uncertainty	Within the measurement range ENR: 4 to 7 dB ±0.02 dB ENR: 12 to 17 dB ±0.025 dB ENR: 20 to 22 dB ±0.03 dB

GAIN Measurement

Measurement range	Within the frequency range -20 to +40 dB
Instrument Uncertainty	Within the measurement range ≤0.07

Resolution Bandwidth

Setting Range

Connector

Output voltage: 28 ±0.5 V, Pulsed	Noise Source	Connector: Rear Panel, BNC-J Output Voltage: 28 ±0.5 V, Pulsed
-----------------------------------	--------------	---

*: Recommending the NC346 Series noise sources by Noisecom company

100 kHz to 8 MHz

Hardware Option (Continuation)

MS2690A/MS2691A/MS2692A-020 Vector Signal Generator

Frequency

Range	125 MHz to 6 GHz
Resolution	0.01 Hz steps

Output Level

Setting range	-140 to +10 dBm (CW), -140 to 0 dBm (Modulation)
Units	dBm, dBµV (Terminated, Open)
Resolution	0.01 dB
Level Accuracy	18° to 28°C, CW Output level: p $-120 \le p \le +5 \text{ dBm}$ $\pm 0.5 \text{ dB}$ $(\le3.0 \text{ GHz})$ $-110 \le p \le +5 \text{ dBm}$ $\pm 0.8 \text{ dB}$ $(>3.0 \text{ GHz})$ $-127 \le p < -120 \text{ dBm}$ $\pm 0.7 \text{ dB}$ $(\le3.0 \text{ GHz})$ $-127 \le p \le -110 \text{ dBm}$ $\pm 2.5 \text{ dB} (typ.)$ $(>3.0 \text{ GHz})$ $-136 \le p < -127 \text{ dBm}$ $\pm 1.5 \text{ dB} (typ.)$ $(>3.0 \text{ GHz})$
Linearity	18° to 28°C, CW, Referenced to -5 dBm outputOutput level: p $-120 \le p \le -5 \text{ dBm}$ $\pm 0.2 \text{ dB}$ (typ.) ($\le 3.0 \text{ GHz}$) $-110 \le p \le -5 \text{ dBm}$ $\pm 0.3 \text{ dB}$ (typ.) (>3.0 GHz)
Connector	N-J connector, 50Ω [Front panel, SG Output (Opt.)]
VSWR	CW: ≤–5 dBm, Modulation: ≤–15 dBm 1.3 (≤3.0 GHz) 1.9 (>3.0 GHz)
Max. Reverse Input	1 W peak (≥300 MHz), 0.25 W peak (<300 MHz)

Signal Purity

Harmonic Spurious	Output level: ≤+5 dBm, CW, Output frequency: ≥300 MHz ≤–30 dBc
Non-harmonic Spurious	Output level: ≤+5 dBm, CW, Offset: ≥15 kHz (from Output frequency) <-68 dBc (125 MHz ≤ Frequency ≤ 500 MHz) <-62 dBc (500 MHz < Frequency ≤ 1.0 GHz) <-56 dBc (1.0 GHz < Frequency ≤ 2.0 GHz) <-50 dBc (2.0 GHz < Frequency ≤ 6.0 GHz)

Vector Modulation

18° to 28°C, SG Level Auto CAL: On

Vector Accuracy Carrier Leak	W-CDMA (DL1code)
	Output level: ≤–5 dBm, Output frequency: 800 MHz to 2700 MHz
	≤2% (ms)
	Output frequency: ≥300 MHz
	≤-40 dBc
Image Rejection	Output frequency: ≥300 MHz, Using 10 MHz max. sine wave
	≤-40 dBc
ACLR	Output level: ≤–5 dBm,
	Using W-CDMA (Test Model 1 64DPCH) signal, 300 MHz ≤ Output frequency ≤ 2.4 GHz
	≤–64 dBc/3.84 MHz (5 MHz offset), ≤–67 dBc/3.84 MHz (10 MHz offset)
CW and Level Error at Vector Modulation	AWGN signal with bandwidth of 5 MHz, Output frequency: ≥300 MHz
	±0.2 dB (Output level: ≤–15 dBm)
	±0.4 dB (typ., –15 dBm < Output level: ≤–5 dBm)
Spectrum Inversion	Supported

Pulse Modulation

On/Off ratio	≥60 dB
Rising/Falling Edge Time	≤90 ns (10 to 90%)
Pulse Repetition Frequency	DC to 1 MHz (Duty 50%)
External Panel Modulation Signal Input	AUX connector (Rear panel), 600 Ω , 0 to 5 V, Threshold value: approx. 1 V

Hardware Option (Continuation) Arbitrary Waveform Generator

Waveform Resolution	14 bits
Marker Output	Three signals (three signals in waveform pattern, or real-time three signals generation), TTL, polarity inversion function
Internal Baseband	Range: 20 kHz to 160 MHz
Reference Clock	Resolution: 0.001 Hz
External Baseband Reference Clock	Range: 20 kHz to 40 MHz Division, Multiplier function: 1, 2, 4, 8, 16, 1/2, 1/4, 1/8, 1/16 of input signal Input connector: AUX connector (Rear panel), 0.7 Vp-p min. (AC/50Ω), or TTL
Waveform Memory	Memory: 256 Msamples
AWGN Addition Function	CN Ratio absolute value: ≤40 dB

BER Measurement

Connector	AUX connector (Rear panel)
Input Level	TTL Level
Input Signal	Data, Clock, Enable
Input Bit Rate	100 bps to 10 Mbps
Measured Patterns	PN9, PN11, PN15, PN20, PN23, ALL0, ALL1, 01 Repeat
Synchronization Establishing Condition	PN Signal: PN stage × 2 bit error free At PNFix Signal: 0 PN stage × 2 bit error free, PN signal and sync establishment, establish sync with PNFix signal at PN stage error free from PNFix signal header bit ALL0, ALL1, 01 Repeat: 10 bit error free User Define: 8 to 1024 bits (variable) error free, Select header bit used at sync detection
Re-synchronization Judgment Condition	x/y y = Measured bit count: Select from 500, 5000, 50000 x = y bit error bit count: Setting range 1 to y/2
Measured Bit Count	$\leq 2^{32} - 1$ bits
Measured Error Bit Count	$\leq 2^{31} - 1$ bits
Measurement End Conditions	Measured bit count, Measured error bit count
Auto Re-synchronization Function	On/Off
Operation at Resync.	Select from Count Clear, and Count Keep
Measurement Mode	Single, Endless, Continuous
Display	Status, Error, Error Rate, Error Count, Sync Loss Count, Measured bit count
Polarity Inversion Function	Data, Clock, Enable polarity inversion
Clear Measurement Function	Clear measured value saved at sync during BER measurement, and select measurement from 0

MS2690A/MS2691A/MS2692A-050 HDD Digitizing Interface

	Bandwidth	Sampling Rate	Recorded Data Format	
Bandwidth, Sampling Rate,	100, 250, 500 kHz, 1, 2.5, 5 MHz	200, 500 kHz, 1, 2, 5, 10 MHz	Floating Decimal Format	
Recorded Data Format	10 MHz, 18.6 MHz	20 MHz	Fixed Decimal Format	
	20 MHz	25 MHz	(16 bits)	
Recording Time	5 seconds to 4 hours			
Number of Recorded File	1000 files max.			
Resample Function	Convert by resampling at data retrieval, Setting range: Sampling rate/2 to Sampling rate			
Trigger Function	Video, Wide IF Video, External, SG Marker			
Count Mode	Capturing times: 1 to 20 times			
	Connector: External Serial ATA Connector	nector		
Interface	Data rate: 1.5 Gbps			
	Hot Plug: Not supported (The main fi	rame and external HDD must be of	f when connecting/disconnect	ting connectors.)

Hardware Option (Continuation)

MS2692A-067 Microwave Preselector Bypass

Bypasses the preselector to improve the RF frequency characteristics and the in-band frequency characteristics. When the preselector option is set to On, the image response elimination filter is bypassed. Therefore, this function is not appropriate for spurious measurement to receive the image response. Microwave Preselector Bypass: On (with MS2692A-067), Microwave Preselector Bypass: Off (with special directions) Cannot install simultaneously with MS2692A-003, MS2692A-008.

Frequency

Frequency Range	6.0 GHz to 26.5 GHz

Amplitude

Ampinuuc		
RF Frequency Characteristics	18°to 28℃, after CAL, Input attenuator: 10 dB, Microwave Preselector Bypass: On	
	±1.0 dB (6.0 GHz ≤ Frequency ≤ 13.5 GHz)	
	±1.5 dB (13.5 GHz < Frequency ≤ 26.5 GHz)	
	* with MS2692A-067, Microwave Preselector Bypass: Off, see Signal Analyzer/Spectrum Analyzer (RF Frequency Characteristics)	
Displayed Average Noise Level (DANL)	18°to 28℃, Detector: Sample, VBW: 1 Hz (Video average), Input attenuator: 0 dB	
	Microwave Preselector Bypass: On or Off	
	–146 dBm/Hz (6.0 GHz ≤ Frequency < 10.0 GHz)	
	–145 dBm/Hz (10.0 GHz ≤ Frequency ≤ 13.5 GHz)	
	–142 dBm/Hz (13.5 GHz < Frequency ≤ 20.0 GHz)	
	–138 dBm/Hz (20.0 GHz < Frequency ≤ 26.5 GHz)	
Image Responses	Microwave Preselector Bypass: Off	
	<–60 dBc (6.0 GHz ≤ Frequency ≤ 26.5 GHz)	

MS2690A/MS2691A/MS2692A-077 Analysis Bandwidth Extension to 62.5 MHz MS2690A/MS2691A/MS2692A-078 Analysis Bandwidth Extension to 125 MHz (Requires Opt. 077)

Common

Bandwidth	with MS269xA-077 Adds the 50 MHz, 62.5 MHz bandwidths to the standard analysis bandwidths.	
	with MS269xA-077/078 Adds the 50, 62.5, 100, and 125 MHz bandwidths to the standard analysis bandwidths.	
	Auto-setting depending on RBW	
Sampling Rate	with MS269xA-077, Bandwidth: >31.25 MHz 100 MHz	
	with MS269xA-077/078, Bandwidth: >31.25 MHz 100 MHz, 200 MHz	
	Set length of capture time	
Capture Time	with MS269xA-077, Bandwidth: >31.25 MHz Min. capture time length: 1 μs (determined depending on analysis bandwidth) Max. capture time length: 500 ms	
	with MS269xA-077/078, Bandwidth: >31.25 MHz Min. capture time length: 500 ns to 1 μs (determined depending on analysis bandwidth) Max. capture time length: 500 ms	
Resolution Bandwidth (RBW)	with MS269xA-077, Bandwidth: >31.25 MHz Setting range: 3 kHz to 3 MHz (1-3 sequence) Selectivity (-60 dB/-3 dB): 4.5:1 (nominal)	
	with MS269xA-077/078, Bandwidth: >31.25 MHz Setting range: 3 kHz to 10 MHz (1-3 sequence) Selectivity (–60 dB/–3 dB): 4.5:1 (nominal)	
ADC Resolution	with MS269xA-077/078, Bandwidth: >31.25 MHz 14 bits	
Frequency	without MS2692A-067, Bandwidth: >31.25 MHz 100 MHz to 6.0 GHz	
	with MS2692A-067, Bandwidth: >31.25 MHz 100 MHz to 26.5 GHz	

Hardware Option (Continuation)

Amplitude

	18° to 28°C, Input attenuator: 0 dB			
	without MS269xA-008, or Preamp: Off,	Frequency band mode	e: Normal	
	Frequency	Max.		
	100 MHz ≤ Frequency < 2.2 GHz	–147.0 [dBm/Hz]		
	2.2 GHz ≤ Frequency < 4.0 GHz	–145.0 [dBm/Hz]		
	4.0 GHz ≤ Frequency ≤ 6.0 GHz	–143.0 [dBm/Hz]		
	with MS269xA-008, Preamp: On, Frequency band mode: Normal			
	Frequency	Max.		
Displayed Average Noise	100 MHz ≤ Frequency < 2.2 GHz	–160.0 [dBm/Hz]		
	2.2 GHz ≤ Frequency < 4.0 GHz	–158.0 [dBm/Hz]		
	4.0 GHz ≤ Frequency ≤ 6.0 GHz	–154.0 [dBm/Hz]		
	with MS2692A-067, Microwave Presele	ector Bypass: On	-	
	Frequency	Max.		
	6.0 GHz < Frequency < 10.0 GHz	–140.0 [dBm/Hz]		
	10.0 GHz ≤ Frequency ≤ 13.5 GHz	–136.0 [dBm/Hz]		
	13.5 GHz < Frequency ≤ 20.0 GHz	–133.0 [dBm/Hz]		
	20.0 GHz < Frequency ≤ 26.5 GHz	–129.0 [dBm/Hz]		
	18° to 28°C, after CAL, Input attenuator	: ≥10 dB, Center frequ	iency, CW, RBW: Auto, Time Detection: Average,	
Total Level Accuracy*	Marker Result: Integration of Peak (Acc	curacy), Excluding the	noise noor effect	
	without MS269xA-008, or Preamp: Off,	Mixer input level: ≤0 d	IBm, Bandwidth: >31.25 MHz	
*: The Total level accuracy is found from root sum of	$\pm 0.5 \text{ dB} (100 \text{ MHz} \le \text{Frequency} \le 6.0$	GHz, Frequency band	d mode: Normal)	
squares (RSS) of RF	with MS269xA-008, Preamp: On, Prean	np input level: ≤–20 dI	Bm, Bandwidth: >31.25 MHz	
characteristics, linearity	$\pm 1.0 \text{ dB} (100 \text{ MHz} \le \text{Frequency} \le 6.0$	GHz, Frequency band	d mode: Normal)	
error, and input attenuator	with MS269xA-077, or MS269xA-077/07	78, Bandwidth: >31.25	5 MHz	
switching error.	with MS2692A-067, Microwave Preselector Bypass: On			
	$\pm 1.8 \text{ dB}$ (6.0 GHz \leq Frequency ≤ 13.5	GHz, Frequency ban	d mode: Normal)	
	$\pm 3.0 \text{ dB}$ (13.5 GHz \leq Frequency ≤ 26 .	5 GHZ)		
	Excluding the holse floor effect			
	without MS269xA-008, or Preamp: Off,	Frequency band mode	e: Normal	
	±0.07 dB (Mixer input level: ≤–20 dBm)			
	+0.30 dB (Mixer input level: <0 dBm F	II) Frequency: <6 0 GHz)		
Linearity Error	with MS260xA 008 Brooms: On Frogu	iongy band mode: Nor	mal	
	+0.07 dB (Mixer input level: <=40 dBm	n)	IIIa	
	+0.10 dB (Mixer input level: \leq -30 dBr	n)		
	±0.50 dB (Mixer input level: ≤–20 dBr	n)		
	with MS2692A-067 Microwave Presele	ector Bypass: On		
	±0.60 dB (Mixer input level: ≤0 dBm, F	Frequency: > 6.0 GHz)	
	18° to 28°C, After CAL, Input attenuator	: 10 dB	,	
	without MS269xA-008, or Preamp: Off			
	± 0.35 dB (100 MHz \leq Frequency \leq 6.0	0 GHz, Frequency bar	nd mode: Normal)	
RF Frequency	with MS269xA-008, Preamp: On			
Characteristics	$\pm 0.65 \text{ dB}$ (100 MHz \leq Frequency ≤ 6.0	0 GHz, Frequency bar	nd mode: Normal)	
	with MS2692A-067, Microwave Presele	ctor Bypass: On		
	±1.0 dB (6.0 GHz < Frequency ≤ 13.5	GHz)		
	$\pm 1.5 \text{ dB}$ (13.5 GHz < Frequency ≤ 26 .	5 GHz)		

Note: Amplitude errors may occur in digitized IQ data at a probability of 0.0001 ppm or less. (AD converter maker nominal specifications) when the Analysis Bandwidth Extension 62.5 MHz/125 MHz option operates at the 50 MHz/62.5 MHz/100 MHz/125 MHz bandwidth setting.

Typical (typ):

Performance not warranted. Must products meet typical performance.

Nominal:

Values not warranted. Included to facilitate application of product.

Example:

Performance not warranted. Data actually measured by randomly selected measuring instruments.

Ordering Information

Please specify the model/order number, name and quantity when ordering. The names listed in the chart below are Order Names. The actual name of the item may differ from the Order Name.

Model/Order No.	Name
	- Main Frame -
MS2690A	Signal Analyzer (50 Hz to 6.0 GHz)
MS2691A	Signal Analyzer (50 Hz to 13 5 GHz)
MS2602A	Signal Analyzer (50 Hz to 26.5 GHz)
IVISZ09ZA	
	- Standard Accessories -
	Power Cord :1 pc
P0031A	USB Memory (>1 GB USB2.0 Flash Driver) :1 pc
Z0541A	USB Mouse :1 pc
	Install CD-ROM
	(Application software instruction manual CD-ROM) 1 pc
	Ontions
M62600A 001	- Options - Dubidium Deference Opeillater (Aging rate 11 + 10 ⁻¹⁰ /menth)
W32090A-001	
MS2690A-008	6 GHZ Preamplifier (100 KHZ to 6 GHZ)
MS2690A-017	Noise Figure Measurement Function
MS2690A-020	Vector Signal Generator (125 MHz to 6 GHz)
MS2690A-050	HDD Digitizing Interface
MS2690A-077	Analysis Bandwidth Extension to 62.5 MHz
MS2690A-078*2	Analysis Bandwidth Extension to 125 MHz
	(Requires MS2690A-077)
MS26904-313	Removable HDD
M626014 004	Publicium Potoronao Oppillator (Aging rate (A
N000044-000	Rubicium Reference Oscillator (Aging rate ±1 x 10 %/month)
INS2691A-003	Extension of Preselector Lower Limit to 3 GHz
	(Extends lower limit of preselector to 3 GHz)
MS2691A-008	6 GHz Preamplifier (100 kHz to 6 GHz)
MS2691A-017	Noise Figure Measurement Function
MS2691A-020	Vector Signal Generator (125 MHz to 6 GHz)
MS2691A-050	HDD Digitizing Interface
MS2691A-077	Analysis Bandwidth Extension to 62.5 MHz
MS2691A-078*2	Analysis Bandwidth Extension to 125 MHz
1110200171010	(Requires MS2691A-077)
MS2601A 212	Pomovable HDD
NO2091A-313	
MS2692A-001	Rubidium Reference Oscillator (Aging rate $\pm 1 \times 10^{-7}$ /month)
MS2692A-003	Extension of Preselector Lower Limit to 3 GHz
	(Extends lower limit of preselector to 3 GHz)
MS2692A-008	6 GHz Preamplifier (100 kHz to 6 GHz)
MS2692A-017	Noise Figure Measurement Function
MS2692A-020	Vector Signal Generator (125 MHz to 6 GHz)
MS2692A-050	HDD Digitizing Interface
MS2692A-067*3	Microwave Preselector Bypass
MS2692A-077	Analysis Bandwidth Extension to 62.5 MHz
MS2692A-078*2	Analysis Bandwidth Extension to 125 MHz
MOLOOLIN OTO	(Requires MS2692A-077)
MS2602A 212	Pomovable HDD
10102032A-313	
	- Retrotit Options -
MS2690A-101	Rubidium Reference Oscillator Retrofit (Aging rate $\pm 1 \times 10^{-10}$ /month)
MS2690A-108	6 GHz Preamplifier Retrofit (100 kHz to 6 GHz)
MS2690A-117	Noise Figure Measurement Function Retrofit
MS2690A-120	Vector Signal Generator Retrofit (125 MHz to 6 GHz)
MS2690A-150	HDD Digitizing Interface Retrofit
MS2690A-177*1	Analysis Bandwidth Extension to 62.5 MHz Retrofit
MS2690A-178*1,*2	Analysis Bandwidth Extension to 125 MHz Retrofit
	(Requires MS2690A-077/177)
MS2690A-180*4	CPU/Windows7 Upgrade Retrofit
MS2601A-101	Rubidium Reference Oscillator Retrofit (Aging rate $\pm 1 \times 10^{-10}$ /month)
MS2601A 102	Extension of Preselector Lower Limit to 2 CHz Detrofit
WS2091A-103	
10000044 400	(Extends lower limit or pre-selector to 3 GHZ)
MS2691A-108	6 GHZ Preamplifier Retrofit (100 kHz to 6 GHz)
MS2691A-117	Noise Figure Measurement Function Retrofit
MS2691A-120	Vector Signal Generator Retrofit (125 MHz to 6 GHz)
MS2691A-150	HDD Digitizing Interface Retrofit
MS2691A-177*1	Analysis Bandwidth Extension to 62.5 MHz Retrofit
MS2691A-178*1,*2	Analysis Bandwidth Extension to 125 MHz Retrofit
	(Requires MS2691A-077/177)
MS2691A-180*4	CPU/Windows7 Upgrade Retrofit

*1: The MS269xA-177/178 cannot be retrofitted to the MS269xA already fitted with the MS269xA-004/104 option (discontinued).

*2: Combining the MS269xA-078 Analysis Bandwidth Extension to 125 MHz and MX269028A-002 wireless LAN IEEE 802.11ac (160 MHz) measurement software (only for MS269xA) supports modulation analysis up to 160-MHz bandwidth signals of the IEEE 802.11ac. See measurement software catalog for more details.

*3: Cannot be installed simultaneously with MS2692A-003/103/008/108 and MS2692A-004/104 option (discontinued).

*4: Contact our sales representative for more details.

Model/Order No	Name
M62602A 101	$\frac{1}{10000000000000000000000000000000000$
MS2692A-101	Extension of Precelector Lower Limit to 2 CHz Potrofit
WI52092A-103	Extension of Preselector Lower Limit to 3 GHZ Retroit
M000004 400	(Extends lower limit of pre-selector to 3 GHz)
MS2692A-108	6 GHZ Preampliner Retrofit (100 kHZ to 6 GHZ)
MS2692A-117	Noise Figure Measurement Function Retrotit
MS2692A-120	Vector Signal Generator Retrofit (125 MHz to 6 GHz)
MS2692A-150	HDD Digitizing Interface Retrofit
MS2692A-167*3	Microwave Preselector Bypass Retrofit
MS2692A-177*	Analysis Bandwidth Extension to 62.5 MHz Retrofit
MS2692A-178*1,*2	Analysis Bandwidth Extension to 125 MHz Retrofit
	(Requires MS2692A-077/177)
MS2692A-180**	CPU/Windows/ Upgrade Retrofit
	- Software Options -
	CD-ROM with License and Operation manuals
MX269010A	Mobile WiMAX Measurement Software
MX269011A	W-CDMA/HSPA Downlink Measurement Software
MX269012A	W-CDMA/HSPA Uplink Measurement Software
MX269013A	GSM/EDGE Measurement Software
MX269013A-001	EDGE EVOlution Measurement Software
MY2600444	(Requires MX269013A)
WX269014A	
WX269015A	Vester Medulation Analysis Software
MX269017A	Vector Modulation Analysis Software
WX269020A	LTE Downlink Measurement Software
WIX269020A-001	LTE-Advanced FDD Downlink Measurement Software
MY260024A	(Requires MA269020A)
NX269021A	LTE Oplink Measurement Software
MY260022A	LTE TOD Downlink Measurement Software
WIX209022A-001	(Poguiros MY260022A)
MX260022A	TE TDD Uplink Massuroment Software
MX269023A	CDMA2000 Forward Link Moasurement Software
MY260024A	All Measure Function (Requires MX260024A)
MX269024A-001	EV-DO Forward Link Measurement Software
MX269026A-001	All Measure Function (Requires MX260026A)
MX269028A	WI AN (802 11) Measurement Software
MX2690280-002*2	802 11ac (160 MHz) Measurement Software
111/1200020/1002	(For MS269xA Requires MX269028A)
MX269030A	W-CDMA BS Measurement Software
MX269901A	HSDPA/HSUPA IQproducer
MX269902A	TDMA IOproducer
MX269904A	Multi-Carrier IQproducer
MX269905A	Mobile WiMAX IQproducer
MX269908A	LTE IQproducer
MX269908A-001	LTE-Advanced FDD Option (Requires MX269908A)
MX269910A	LTE TDD IQproducer
MX269910A-001	LTE-Advanced TDD Option (Requires MX269910A)
MX269911A	WLAN IQproducer
MX269911A-001	802.11ac (80 MHz) Option (Requires MX269911A)
MX269912A	TD-SCDMA IQproducer
MX269970A	1xEV-DO Reverse Receiver Test Waveform Pattern
	- Other Software Options -
	These software are for PC.
MX705010A	Wi-SUN PHY Measurement Software
MX705110A	Wi-SUN Protocol Monitor
	- Warranty Service -
MS2690A-ES210	2 Years Extended Warranty Service
MS2690A-ES310	3 Years Extended Warranty Service
MS2690A-ES510	5 Years Extended Warranty Service
MS2691A-ES210	2 Years Extended Warranty Service
MS2691A-ES310	3 Years Extended Warranty Service
MS2691A-ES510	5 Years Extended Warranty Service
MS2692A-ES210	2 Years Extended Warranty Service
MS2692A-ES310	3 Years Extended Warranty Service
MS2692A-ES510	5 Years Extended Warranty Service

Model/Order No.	Name		
	- Application Parts -		
	Following operation manuals provided as hard copy		
W2850AE	MS2690A/MS2691A/MS2692A Operation Manual		
	(Main frame Operation)		
W2851AF	MS2690A/MS2691A/MS2692A Operation Manual		
	(Main frame Remote Control)		
10/295245	(Main frame Remote Control)		
VVZOJZAE	(Girael Arekare Exection Operation)		
	(Signal Analyzer Function Operation)		
W2853AE	MS2690A/MS2691A/MS2692A Operation Manual		
	(Signal Analyzer Function Remote Control)		
W2854AE	MS2690A/MS2691A/MS2692A Operation Manual		
	(Spectrum Analyzer Function Operation)		
W2855AE	MS2690A/MS2691A/MS2692A Operation Manual		
	(Spectrum Analyzer Function Remote Control)		
W2856AE	MS2690A/MS2691A/MS2692A-020 Operation Manual		
	(Operation)		
W2857AF	MS2690A/MS2691A/MS2692A-020 Operation Manual		
	(Remote Control)		
	(Remote Control)		
WZ914AE			
	(IQproducer)		
W2929AE	MS2690A/MS2691A/MS2692A-020 Operation Manual		
	(Standard Waveform Pattern)		
W3130AE	MS2690A/MS2691A/MS2692A-040 Operation Manual		
	(Operation)		
W3117AE	Phase Noise Measurement Function Operation Manual		
	(Operation)		
W3118AE	Phase Noise Measurement Function Operation Manual		
	(Remote control)		
W3655AF	MS2690A/MS2691A/MS2692A and MS2830A		
	Operation Manual		
	(Noise Figure Measurement Function Operation)		
MOREGAE			
W3030AE	MS2090A/MS209TA/MS2092A and MS2030A		
	Operation Manual		
	(Noise Figure Measurement Function Remote control)		
W2919AE	MX269010A Operation Manual (Operation)		
W2954AE	MX269010A Operation Manual (Remote Control)		
W3098AE	MX269011A Operation Manual (Operation)		
W3099AE	MX269011A Operation Manual (Remote control)		
W3060AE	MX269012A Operation Manual (Operation)		
W3061AE	MX269012A Operation Manual (Remote control)		
W3100AE	MX269013A Operation Manual (Operation)		
W3101AE	MX269013A Operation Manual (Remote control)		
W3031AE	MX269014A Operation Manual (Operation)		
W3032AF	MX269014A Operation Manual (Remote control)		
W3044AE	MX269015A Operation Manual (Operation)		
W3045AE	MX269015A Operation Manual (Operation)		
10040AL	MX269013A Operation Manual (Remote control)		
W3305AE	MX200017A Operation Manual (Operation)		
W3300AE	My2090017A Operation Ivianual (Remote control)		
W3014AE	MX209020A Operation Manual (Operation)		
W3064AE	MX269020A Operation Manual (Remote control)		
W3015AE	MX269021A Operation Manual (Operation)		
W3065AE	MX269021A Operation Manual (Remote control)		
W3209AE	MX269022A Operation Manual (Operation)		
W3210AE	MX269022A Operation Manual (Remote control)		
W3521AE	MX269023A Operation Manual (Operation)		
W3522AE	MX269023A Operation Manual (Remote Control)		
W3201AE	MX269024A Operation Manual (Operation)		
W3202AE	MX269024A Operation Manual (Remote control)		
W3203AE	MX269026A Operation Manual (Operation)		
W3204AF	MX269026A Operation Manual (Remote control)		
W3528AF	MX269028A Operation Manual (Operation)		
W/3520AE	MX260028A Operation Manual (Operation)		
W/2860AE	MX260020A Operation Manual (Cremole Control)		
W200UAE			
W2861AE	MX209030A Operation Manual (Remote control)		
W3108AE	IVIA∠09050A Operation Manual (Operation)		
W3109AE	MX269050A Operation Manual (Remote control)		
W2915AE	MX269901A Operation Manual		
W2916AE	MX269902A Operation Manual		
W2917AE	MX269904A Operation Manual		
W2918AE	MX269905A Operation Manual		
W3023AE	MX269908A Operation Manual		
W3221AF	MX269910A Operation Manual		
W3488AF	MX269911A Operation Manual		
W/35824F	MX269912A Operation Manual		
W/3675AE	MX260070A Operation Manual		
W3075AE			

Model/Order No.	Name
K240B	Power Divider
	(K connector, DC to 26.5 GHz, 50Ω, K-J, 1 W max)
MA1612A	Four-Port Junction Pad (5 MHz to 3 GHz, N-J)
MP752A	Termination (DC to 12.4 GHz, 50Ω, N-P)
MA2512A	Band Pass Filter (for W-CDMA, 1.92 to 2.17 GHz)
J0576B	Coaxial Cord (N-P · 5D-2W · N-P), 1 m
J0576D	Coaxial Cord (N-P · 5D-2W · N-P), 2 m
J0127A	Coaxial Cord (BNC-P · RG58A/U · BNC-P), 1 m
J0127B	Coaxial Cord (BNC-P · RG58A/U · BNC-P), 2 m
J0127C	Coaxial Cord (BNC-P · RG58A/U · BNC-P), 0.5 m
J0322A	Coaxial Cord (SMA-P · 50Ω SUCOFLEX104 · SMA-P), 0.5 m (DC to 18 GHz)
J0322B	Coaxial Cord (SMA-P · 50Ω SUCOFLEX104 · SMA-P), 1 m (DC to 18 GHz)
J0322C	Coaxial Cord (SMA-P · 50Ω SUCOFLEX104 · SMA-P), 1.5 m (DC to 18 GHz)
J0322D	Coaxial Cord (SMA-P \cdot 50 Ω SUCOFLEX104 \cdot SMA-P),
10905	2 m (DC to 18 GHz)
00805	UC BIOCK, N Type (MODEL 7003) (10 kHz to 18 GHz, N-P · N-J)
J1554A	DC Block, SMA type (MODEL 7006)
	(9 kHz to 26.5 GHz, SMA-P · SMA-J)
J1555A	DC Block, SMA type (MODEL 7006-1)
K064	$(9 \text{ KHZ to } 20 \text{ GHZ}, \text{SMA-P} \cdot \text{SMA-J})$
N201	DC BIOCK (10 KHZ to 40 GHZ, K-P · K-J)
J0004	Coaxial Adapter (DC to 12.4 GHz, 50Ω , N-P \cdot SMA-J)
J1396A	N-SMA Adapter (DC to 26.5 GHz, 50 Ω , N-P · SMA-J)
10911	(Do to 40 OUE suggest 4 m)
10012	(5F102A, 11K254/K254/1.000)
J0912	
	(DC to 40 GHz, approx. 0.5 m) (SE102A_11K254/K254/0 5M)
41KC-3	Eived Attenuator 3 dB (DC to 40 GHz 3 dB)
112614	Ethernet Cable (Shield type, straight) 1 m
11261R	Ethernet Cable (Shield type, straight), 7 m
11261C	Ethernet Cable (Shield type, straight), 5 m
.11261D	Ethernet Cable (Shield type, cross), 3 m
.10008	GPIB Connection Cable 2.0 m
.11373A*	ALLX Conversion Adapter
	(AUX \rightarrow BNC for vector signal generator option)
B0597A	Rack Mount Kit (FIA)
B0589A	Carrying Case (Hard type, with casters)
B0633A	Carrying Case (Soft type)
Z1082A	10/13 MHz Reference Signal Input
MA24105A	Inline Peak Power Sensor
	(350 MHz to 4 GHz, with USB A to mini B cable)
MA24106A	USB Power Sensor
	(50 MHz to 6 GHz, with USB A to mini B cable)
MA24108A	Microwave USB Power Sensor
	(10 MHz to 8 GHz, with USB A to Micro-B cable)
MA24118A	Microwave USB Power Sensor
	(10 MHz to 18 GHz, with USB A to Micro-B cable)
MA24126A	Microwave USB Power Sensor (10 MHz to 26 GHz, with USB A to Micro-B coblo)
71037A	Installation Kit
	(required when retrofitting options or installing software)

*: The J1373A AUX Conversion Adapter is not a standard accessory for the MS269xA-020/120 Vector Signal Generator Option.

B0633A Carrying Case (Soft type)

J1373A AUX Conversion Adapter

Trademarks:

- IQproducer[™] is a registered trademark of Anritsu Corporation.
- \bullet MATLAB $^{\otimes}$ is a registered trademark of The MathWorks, Inc.
- CDMA2000® is a registered trademark of the Telecommunications Industry Association (TIA-USA).
- The Bluetooth® mark and logos are owned by Bluetooth SIG, Inc. and are used by Anritsu under license.

MA24106A

USB Power Sensor

- Pentium® is registered trademarks of Intel Corporation or its subsidiaries in the USA and other countries.
- Windows® is a registered trademark of Microsoft Corporation in the USA and other countries.
- CompactFlash® is a registered trademark of SanDisk Corporation in the United States and is licensed to CFA (Compact Flash Association).
- WiMAX® is a trademark or registered trademark of WiMAX Forum.
- Wi-SUN® is a registered trademark of Wi-SUN Alliance.
- $\mbox{-}\mbox{Wi-Fi}^{\mbox{\tiny B}}$ is a registered trademark of Wi-Fi Alliance.
- Other companies, product names and service names are registered trademarks of their respective companies.

<u>/Inritsu</u>

• United States Anritsu Company

Ti155 East Collins Blvd., Suite 100, Richardson, TX 75081, U.S.A. Toll Free: 1-800-267-4878 Phone: 41-972-644-1777 Fax: +1-972-641-1877

Canada
 Apritou Ele

Anritsu Electronics Ltd. 700 Silver Seven Road, Suite 120, Kanata, Ontario K2V 1C3, Canada Phone: +1-613-591-2003 Fax: +1-613-591-1006

Brazil

Anritsu Eletrônica Ltda. Praça Amadeu Amaral, 27 - 1 Andar 01327-010 - Bela Vista - São Paulo - SP - Brazil

01327-010 - Bela Vista - São Paulo - SP - Brazil Phone: +55-11-3283-2511 Fax: +55-11-3288-6940

Mexico
 Anritsu Company, S.A. de C.V.
 Av. Ejército Nacional No. 579 Piso 9, Col. Granada
 11520 México, D.F., México
 Phone: +52-55-1101-2370
 Fax: +52-55-5254-3147

United Kingdom
 Anritsu EMEA Ltd.
200 Capability Green, Luton, Bedfordshire, LU1 3LU, U.K.
Phone: +44-1582-433200
 Fax: +44-1582-731303

• France Anritsu S.A. 12 avenue du Québec, Bâtiment Iris 1- Silic 612, 91140 VILLEBON SUR YVETTE, France Phone: +33-1-60-92-15-50 Fax: +33-1-64-46-10-65

• Germany Anritsu GmbH Nemetschek Haus, Konrad-Zuse-Platz 1 81829 München, Germany Phone: +49-89-442308-0 Fax: +49-89-442308-55

• Italy

Anritsu S.r.I. Via Elio Vittorini 129, 00144 Roma, Italy Phone: +39-6-509-9711 Fax: +39-6-502-2425

Sweden

Anritsu AB Kistagången 20B, 164 40 KISTA, Sweden Phone: +46-8-534-707-00 Fax: +46-8-534-707-30

• Finland Anritsu AB Teknobulevardi 3-5, FI-01530 VANTAA, Finland Phone: +358-20-741-8100 Fax: +358-20-741-8111

Denmark
 Anritsu A/S
 Kay Fiskers Plads 9, 2300 Copenhagen S, Denmark
 Phone: +45-7211-2200
 Fax: +45-7211-2210

Russia

Anritsu EMEA Ltd. Representation Office in Russia Tverskaya str. 16/2, bld. 1, 7th floor. Russia, 125009, Moscow Phone: +7-495-363-1694 Fax: +7-495-363-1694 Fax: +7-495-935-8962

• United Arab Emirates Anritsu EMEA Ltd. Dubai Liaison Office

P O Box 500413 - Dubai Internet City Al Thuraya Building, Tower 1, Suit 701, 7th Floor Dubai, United Arab Emirates Phone: +971-4-3670352 Fax: +971-4-3688460

India

Anritsu India Private Limited 2nd & 3rd Floor, #837/1, Binamangla 1st Stage, Indiranagar, 100ft Road, Bangalore - 560038, India Phone: +91-80-4058-1300 Fax: +91-80-4058-1301 Specifications are subject to change without notice.

Singapore

B0589A

Carrying Case (Hard type)

Anritsu Pte. Ltd. 11 Chang Charn Road, #04-01, Shriro House Singapore 159640 Phone: +65-6282-2400 Fax: +65-6282-2533

• P.R. China (Shanghai)

Anritsu (China) Co., Ltd. Room 2701-2705, Tower A, New Caohejing International Business Center No. 391 Gui Ping Road Shanghai, 200233, P.R. China Phone: +86-21-6237-0898 Fax: +86-21-6237-0899

• P.R. China (Hong Kong) Anritsu Company Ltd.

Unit 1006-7, 10/F., Greenfield Tower, Concordia Plaza, No. 1 Science Museum Road, Tsim Sha Tsui East, Kowloon, Hong Kong, P.R. China Phone: +852-2301-4980 Fax: +852-2301-3545

• Japan Anritsu Corporation 8-5, Tamura-cho, Atsugi-shi, Kanagawa, 243-0016 Japan Phone: +81-46-296-1221 Fax: +81-46-296-1238

Korea

Anritsu Corporation, Ltd.

5FL, 235 Pangyoyeok-ro, Bundang-gu, Seongnam-si, Gyeonggi-do, 463-400 Korea Phone: +82-31-696-7750 Fax: +82-31-696-7751

Australia

Anritsu Pty. Ltd. Unit 21/270 Ferntree Gully Road, Notting Hill, Victoria 3168, Australia Phone: +61-3-9558-8177 Fax: +61-3-9558-8255

Taiwan

Anritsu Company Inc. 7F, No. 316, Sec. 1, NeiHu Rd., Taipei 114, Taiwan Phone: +886-2-8751-1816 Fax: +886-2-8751-1817

1404