

## 2-Way Power Divider/Combiner

# **QPD2-2-500-1-S** 2-Way, 0.002~0.5GHz

Features: \* Small Size \* Low Insertion Loss

- Applications:
- \* Amplifiers
- \* Mixers
- \* Antennas
- \* Laboratory Test

### Electrical

Frequency:	0.002~0.5GHz
Insertion Loss:	0.6dB max.
Input VSWR:	1.3 max.
Output VSWR:	1.3 max.
Isolation:	20dB min.
Amplitude Balance:	±0.3dB
Phase Balance:	±2°
Impedance:	50Ω
Average Power:	1W max.
	0.5W max. as combiner

#### Mechanical


Size <sup>*1</sup> :	28*28*12.7mm
	1.102*1.102*0.5in
Weight:	45g
Connectors:	SMA Female
Mounting:	2-Ф2.8mm through-hole


[1] Exclude connectors.

### Environmental

Operation Temperature: -35~+75°C

## **Outline Drawings**





Unit: mm [in] Tolerance: ±0.5mm [±0.02in]

How To Order QPD2-2-500-1-S

Customization is available upon request.