

## 8-Way Power Divider/Combiner

# **QPD8-5-1000-50-S** 8-Way, 0.005~1GHz

Features: \* Small Size \* Low Insertion Loss

- Applications:
- \* Amplifiers
- \* Mixers
- \* Antennas \* Laboratory Test

164\*126\*26mm

SMA Female

6.457\*4.961\*1.024in

4-Φ4.5mm through-hole

#### Electrical


Frequency:	0.005~1GHz
Insertion Loss:	1.6dB max.
VSWR:	1.5 max.
Isolation:	12dB min.
Amplitude Balance:	±0.2dB
Phase Balance:	±5°
Average Power:	50W

#### Mechanical

Size<sup>\*1</sup>: Connectors: Mounting:

[1] Exclude connectors.

#### **Outline Drawings**



Unit: mm [in] Tolerance: ±0.5mm [±0.02in]

### How To Order QPD8-5-1000-50-S

Customization is available upon request.